# Inductor







## **Specifications:**

Inductance : 10µH Inductance Tolerance : ± 20% DC Resistance Max : 0.1Ω DC Current Rating : 1.44A Inductor Case Style : SMD No. of Pins Lead Spacing : 2mm Core Material : Ferrite External Depth : 5.2mm External Length / Height : 4.5mm External Width : 5.8mm Resonant Frequency : 100kHz Series : MCSD54

### **Electrical Characteristics (at 25°C)**

100kHz 0.25V	L	10μH ±20%
at 25°C	DCR	100mΩ (Max.)
100kHz 0.25V Irms = 1.44A	ΔΤ	Temperature Rise 40°C (Max.)

Operating temperature: -55°C to +130°C

#### **Material List**


No.	Item	Material Description
1	Core	R5A CDR5.8 × 4.5(ST) B2.4 F2.3
2	Wire	Ø0.25mm × 1P 2UEWF 155°C
3	Solder (Lead Free)	Sn99.3%/Cu0.7%



# **Inductor**




## **Schematic Diagram**




#### Note:

- 1. Wire Ø0.25mm × 1P 2UEWF 155°C
- 2. 17.5TS (Reference)

### **Electric Characteristics**







# Inductor



### **Configurations and Dimensions**





Dimensions: Millimetres

А	5.2 ±0.3mm	-
В	5.8 ±0.3mm	-
С	4.5 ±0.35mm	-
D	2mm	(Reference)
E	5.8 ±0.5mm	-

#### **Part Number Table**

Description	Part Number
Inductor, 10µH, 1.44A, 20%	MCSD54-100MU

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

