

# Card

## Serial, PCI, RS232, 1Port

pro-SIGNAL



### Description:

This card provides 1 industry standard 9 pin RS232 serial COM port in a single PCI slot. As PCI is fully Plug & Play compatible the operating system or BIOS automatically configures the card ensuring conflict free installation.

### Features:

- 1 × 9 pin, D type RS232 Serial Port
- PCI Bus - Fully Plug & Play
- PCI 2.3 Compliant
- 16 Byte transmit and receive FIFO
- Supports both 3.3V / 5V standards
- Drivers for all popular operating systems
- Test software provided
- Install guide, FAQ and other support documents provided

### Specifications:

UART	: 16550
Speed	: 115,200 maximum baud rate
Data Bits	: 5, 6, 7 or 8
Stop Bits	: 1 or 2
Parity	: odd, even, none, mark or space
Bus type	: 32-bit PCI
IRQs	: Plug and play - Shared interrupts for all ports
Connector Type A	: PCI Slot
Connector Type B	: 1 × RS232 Serial COM
Interface Type	: PCI / RS-232
Kit Contents Descriptive	: Card, test software and user guide
Operating System Software	: Microsoft Win 2000/XP/2003

### Operating Systems:

Windows 7 32bit & 64bit  
Windows Vista 32bit & 64bit  
Windows XP 32bit & 64bit  
Windows Server 2003 & Windows Server 2008  
Windows 2000

### Part Number Table

Description	Part Number
Card, Serial, PCI, RS232, 1Port	PPC202

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of the Group. © Premier Farnell plc 2012.