
Spade (Fork) Tongue Terminal





Specifications:

Connector Type	: Fork / Spade Tongue
Termination Method	: Crimp
Stud/Tab Size	: #6
Wire Size	: 22AWG to 18AWG
Contact Material	: Copper
Contact Plating	: Tin
Insulator Material	: PVC



Part Number Table

	Stud Size	S	w	т	М	Color	Seam	Part Number
16 ~ 14	#6 (0.138)	0.148					Butted	CBS-TV-1406
16 ~ 14	#8 (164)	0.174	0.30	0.09	0.17	Blue		CBS-TV-1408
16 ~ 14	#10 (0.190)	0.2						CBS-TV-1410
22 ~ 18	#4 (0.112)	0.12	0.25					CBS-TV-1804
22 ~ 18	#6 (0.138)	0.148		0.07 0.145	Ded	Seam	CBS-TV-1806	
22 ~ 18	#8 (0.164)	0.174	0.30 0.0		0.145	Rea		CBS-TV-1808
22 ~ 18	#10 (0.190)	0.2						CBS-TV-1810
16 ~ 14	#6 (0.138)	0.148		0.09	0.17	Blue	Brazed Seam	CBS-ZV-1406
16 ~ 14	#8 (164)	0.174						CBS-ZV-1408
16 ~ 14	#10 (0.190)	0.2						CBS-ZV-1410
22 ~ 18	#6 (0.112)	0.148		0.07	0.145	Red		CBS-ZV-1806
22 ~ 18	#8 (0.138)	0.174						CBS-ZV-1808
22 ~ 18	#10 (0.164)	0.2						CBS-ZV-1810
	$ \begin{array}{c} 16 \sim 14 \\ 22 \sim 18 \\ 22 \sim 18 \\ 22 \sim 18 \\ 22 \sim 18 \\ 16 \sim 14 \\ 16 \sim 14 \\ 16 \sim 14 \\ 16 \sim 14 \\ 22 \sim 18 \\ 22 \sim 18 \\ 22 \sim 18 \\ 22 \sim 18 \\ \end{array} $	$16 \sim 14$ #10 (0.190) $22 \sim 18$ #4 (0.112) $22 \sim 18$ #6 (0.138) $22 \sim 18$ #8 (0.164) $22 \sim 18$ #10 (0.190) $16 \sim 14$ #6 (0.138) $16 \sim 14$ #8 (164) $16 \sim 14$ #10 (0.190) $22 \sim 18$ #6 (0.112) $22 \sim 18$ #8 (0.138)	$16 \sim 14$ #10 (0.190)0.2 $22 \sim 18$ #4 (0.112)0.12 $22 \sim 18$ #6 (0.138)0.148 $22 \sim 18$ #8 (0.164)0.174 $22 \sim 18$ #10 (0.190)0.2 $16 \sim 14$ #6 (0.138)0.148 $16 \sim 14$ #8 (164)0.174 $16 \sim 14$ #8 (164)0.174 $16 \sim 14$ #8 (164)0.174 $16 \sim 14$ #8 (0.190)0.2 $22 \sim 18$ #6 (0.112)0.148 $22 \sim 18$ #8 (0.138)0.174	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

