

# Heavy Duty 25 Amp Power Supply



## Description

High current supply is a popular choice for servicing automotive electronic devices and communications equipment. Variable 3V DC to 15V DC voltage range is suitable in a wide range of troubleshooting and repair applications. Efficient switch mode design provides high output current in a compact lightweight package. Whisper quiet fan cooling ensures reliable, long-term operation. Front panel 3/16" diameter binding posts accepts banana plugs or spade terminals, providing convenient access for loads up to 25A.



## Features

- Bright Dual LED displays
- Large 5/8" digits
- Simultaneously shows output voltage and current
- Display accuracy to 0.1V, 0.1A
- Excellent load and line regulation
- Low ripple and noise
- Overvoltage, overload, temperature and short circuit protection
- Detachable IEC power cord

## Specifications:

Output Voltage	: 3V DC to 15V DC
Output Current	: 25A
Load regulation	: 200mV
Line regulation	: 50mV $\pm$ 10%
Ripple and noise	: 5mV (RMS)
Power requirements	: 120V AC, 60Hz
Dimensions	: 4 1/4" (H) x 8 3/4" (W) x 8 3/4" (D)
Weight	: 6.6 lbs.

## Part Number Table

Description	Part Number
Heavy Duty 25 Amp Power Supply	72-7670

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

