Adaptor **SMB Plug to Plug**





Specifications:

Connector Type Connector Type A Connector Type B **Contact Material Contact Material**

Contact Plating Contact Plating **Contact Resistance** Impedance Insulation Resistance Insulator Material No. of Mating Cycles Operating Frequency Max **Operating Temperature** Working Voltage Part to be clean and free of burrs.

: SMB Plug : SMB Plug : Beryllium Copper : Male - Brass Female - Beryllium Copper : Gold : Gold over Nickel : 6mΩ

: Inter Series Coaxial

: 50Ω

: 1,000MΩ

: PTFE

: 500

:4GHz : -65°C to +165°C

: 250V

Connector interface per MIL-STD-348A.

6. <u>35 (0.250) Hexagon</u>			$\neg \vdash$	\Box		
6. <u>35 (0.25</u> (
	15.9 ±0.5 (0.626 ±0.020)					

Dimensions : Millimetres (Inches)

Number	Description	Material	Finish	
1	Spring	Beryllium Copper	Gold	
2	Shell	Brass	Gold 3µ" Mini.	
3	Insulation	PTFE	None	
4	Centre Contact	Beryllium Copper	Gold 30µ" Min.	
5	Body	Draga	Gold 3µ" Min.	
6	Washer	Brass		
7	Insulation	PTFE	None	

Part Number Table

Description	Part Number	
Adaptor, SMB Plug to Plug	24-15-1-TGG	

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

