



Specifications:

No. of Outputs	: 1
Output Connector	: Various
Applications	: General Purpose
Efficiency	: 84%
External Width	: 58mm
Mounting Type	: Desktop
Power Supply Type	: Switch Mode

Input Requirements:

Input Voltage	: 110 to 240V AC
Frequency	: 50/60Hz
Inrush Current	: 40A peak at 120V AC 80A peak at 240V AC
Max. Input Current	: 1.5A at 100V AC

Efficiency:

84% Min. at Full Load Condition.

Total Output Power	: 96W
--------------------	-------

Output Requirements:

Output Voltage	: 16 to 19V DC (Adjustable)
Output Current	: 4A to 5A
Line Regulation	: $\pm 2\%$
Load Regulation : $\pm 5\%$	
Ripple/Noise	: +5% of Output Voltage

Protection:

Current Limit Protection	: Built-in
Over Voltage Protection	: Built-in
Short Circuit Protection	: Built-in

Environmental:

Temperature Range

Operation Temperature : 0°C to +30°C
Storage Temperature : +10°C to +75°C

Humidity:

Operation Humidity : 10% to 90%
Storage Humidity : 10% to 100%

Physical:

PCB Dimension : (L) 127mm × (W) 52mm (H) × 1.2mm.
Case Dimension : (L) 133mm × (W) 58mm (H) × 31mm
Output DC Power Cable : 1.2m

Included Tips

TIP A19

Output : 19V
Dimension : Ø6 × Ø1.4 × 25.5 × (Length) 11mm

TIP B16

Output : 16V
Dimension : Ø6.5 × Ø3 × 22 × (Length) 11mm

TIP C19

Output : 19V
Dimension : Ø5.5 × Ø2.5 × 22.5 × (Length) 11mm

TIP D19

Output : 19V
Dimension : Ø5.5 × Ø2.1 × 22.5 × (Length) 11mm

TIP E19

Output : 19V
Dimension : Ø4.75 × Ø1.7 × 22 × (Length) 11mm

Part Number Table

Description	Part Number
PSU, Desktop, 96W, 16V to 19V	ATD96W

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.