
# Surface Mount Fast Switching Diode





#### Features:

- · Fast Switching Speed
- · For General Purpose Switching Application
- · Ultra-Small Surface Mount Package



### **Applications:**

For general purpose switching application

**SOT-363** 

### Max. Rating @ TA = 25°C unless otherwise specified

Parameter	Symbol	Limits	Unit
DC reverse voltage	VR	85	V
Forward continuous current	lғм	200	mA
Average rectified output current	lo	150	mA
Power dissipation	Po	200	mW
Thermal resistance, junction to ambient	Røja	625	°C/W
Operating and storage temperature range	Т <sub>і,</sub> Тsтg	-65 to +150	°C

### Electrical Characteristics @ TA = 25°C unless otherwise specified


Parameter	Symbol	Conditions	Min.	Max.	Unit
Reverse breakdown voltage	V(BR)R	IR = 100μA	85	-	V
Forward voltage	VF	IF = 1mA IF = 10mA IF = 50mA IF = 150mA	-	0.9 1.0 1.1 1.25	V
Junction capacitance	Cı	V <sub>R</sub> = 0V, f = 1MHz	-	2	pF
Reverse recovery time	trr	I <sub>F</sub> = I <sub>R</sub> = 10mA, Irr = 0.1 × I <sub>R</sub> , R <sub>L</sub> = 100Ω	-	3	ns





## Surface Mount Fast Switching Diode




Typical Characteristics @ TA = 25°C unless otherwise specified










# Surface Mount Fast Switching Diode




### Plastic surface mounted package



SOT-363			
Dim	Min	Max	
Α	1.8	2.2	
В	1.15	1.35	
С	1 Typical		
D	0.1	0.3	
E	0.25	0.4	
G	0.65 Typical		
Н	0.02	0.1	
J	0.1Typical		
К	2.1	2.3	
All Dimensions in mm			

### **Soldering Footprint**



Unit: mm

### **Package Information**

Device	Package	Shipping
BAV199DW-7-F	SOT-363	3,000 / Tape & Reel

#### **Part Number Table**

Description	Part Number	
Surface Mount Fast Switching Diode	BAV199DW-7-F	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

