

# Multimeter Digital



## Specifications:

Basic Functions	Range	Best Accuracy
DC Voltage	4V/40V/400V/1,000V	$\pm(0.5\%+3)$
AC Voltage	4V/40V/400V/1,000V	$\pm(1\%+3)$
DC Millivoltage	40mV/400mV	$\pm(0.8\%+3)$
DC Current	400 $\mu$ A/4,000 $\mu$ A/40mA/400mA/4A/10A	$\pm(1\%+2)$
AC Current	400 $\mu$ A/4,000 $\mu$ A/40mA/400mA/4A/10A	$\pm(1.2\%+5)$
Resistance	400 $\Omega$ /4k $\Omega$ /40k $\Omega$ /400k $\Omega$ /4M $\Omega$ /40M $\Omega$	$\pm(1\%+5)$
Capacitance	10nF/100nF/1,000nF/10 $\mu$ F/100 $\mu$ F	$\pm(3\%+5)$
Frequency	10Hz - 1MHz	$\pm(0.1\%+4)$

## Special Functions

Auto Ranging	-	✓
Dwell	4Cyl / 6Cyl / 8Cyl	$\pm(3\%+5)$
Tach	4Cyl / 6Cyl / 8Cyl	$\pm(3\%+5)$
Diode	-	✓
Continuity Buzzer	-	✓
Max / Min Mode	-	✓
Data Hold	-	✓
Sleep Mode	-	✓
Display Backlight	-	✓
RS232 (USB)	-	✓
Low Battery Display	-	✓
Input Impedance for DC Voltage Measurement	$\geq 10M$	✓
Max. Display	3,999	✓



# Multimeter Digital



## General Characteristics

Power	: 9V Battery (6F22)
LCD Size	: 65 × 43mm
Product Colour	: Orange and Grey
Product Net Weight	: 362g
Product Size	: 180 × 87 × 47mm
Standard Accessories	: Test Lead, Battery, English Manual, RS232 Interface Cable, Software, Alligator Clip
Optional Accessories*	: USB Interface Cable
Standard Individual Packing	: Gift Box
Standard Quantity Per Carton	: 20pcs
Standard Carton Gross Weight	: 465 × 335 × 345mm (0.054 CBM Per Export Carton)
Standard Carton Measurement	: 15kg

\* Specifications and other information are subject to change without further

## Part Number Table

Description	Part Number
Multimeter, Digital, Automotive, Auto	72-9280

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

