

Soldering Station



Features:

- New appearance; light and handy handle, convenient for long-time operation
- Heater with improved temperature material; made through advanced technology and long life
- Computerised temperature correction to calibrate the temperature difference between the soldering tip and display temperature
- Same as the soldering tips of international brand; optional soldering tips according to the different working conditions of users
- Made of conductive materials; anti-static

Specifications:

Input voltage	: 220V AC \pm 10%, 50 Hz
Output voltage	: 24V AC
Power consumption	: 60W / 80W / 100W
Temperature-controlling range	: 150°C to 450°C
Temperature stability	: \pm 1°C (static working mode)
Ground impedance	: < 2 Ω
Ground voltage	: < 2mV
Dimension	: 167mm \times 160mm \times 113 mm

Soldering Iron:

Measurement	: 240mm \times 40mm \times 60mm
Gross weight	: 0.125Kg
Compatible for	: AT60D

Accessories:

ATTEN 907 handle	: 1 pc
Iron holder	: 1 pc
Clean sponge	: 1 pc
Heating elements (2 cores, 60 W)	: Optional



Ceramic heating element, 2 cores, 60W

Part Number Table

Description	Part Number
Soldering Iron, 60W, 220V/110V	AT907-60D
Soldering Station, Digital, EU Plug	AT60D-EU
Soldering Station, Digital, UK Plug	AT60D-UK

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

