

# 60W Dual Soldering Station



## Description:

This advanced station has the features and quality expected by professionals, but provides a fantastic value for hobbyists and educational users.

A clear high-contrast LCD display and simple controls provide a easy user interface.

The thermostat-controlled 60-watt output of this unit provides quick heat up with outstanding precision.

## Features:

- High contrast LCD
- Lead free and ROHS compliant
- Temperature range: 302~842°F (150~450°C)
- Temperature stability  $\pm 1^{\circ}\text{C}$
- F or C selectable readout
- Three programmable presets
- ESD Safe
- Lightweight iron handle
- Long-life ceramic heating element (Replacement iron assembly: 21-11435)
- Includes one tip and soldering stand with cleaning sponge

## Replacement Tips:

MCM Part #	Description	Tip size
21-10140	Small chisel	0.8mm
21-10142	Small chisel	1.2mm
21-10144	Small chisel	1.6mm
21-10146	Small chisel	2.4mm
21-10148	Conical	0.5mm
21-10150	Conical	0.2mm
21-10152	Angled chisel	2mm
21-10154	Angled chisel	3mm
21-10156	Angled chisel	4mm
21-10158	Micro conical	0.2mm

## Part Number Table

Description	Part Number
Advanced Digital Soldering Station	21-10120

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

