<u>Tenma 72-10208 Combustible Gas Leak Detector</u>

eatures
igher Sensitivity
djustable tick rate to locate leaks quickly and easily
isual leak detection by LED indicators
recision sensor detects even the smallest leaks.
ast response of less than two seconds to 40% LEL.
cludes earphone Jack
5" gooseneck

Specifications	
Sensitivity	50 ppm methane
Sensor Type	Low power semiconductor
Warm Up Time	Approx. 60 seconds
Response Time	Less than 2 sec. (up to 40% LEL)
Duty Cycle	Continuous
Probe Length	16"
Power Supply	3 "C" cell batteries
Battery Life	8 hours continuous use, typical
Alarm	Visible & Audible at 10% LEL for Methane. Can be calibrated
	for other concentrations or gases
Warranty	1 year
Operating Conditions	
To ensure accurate readings use it	only when ambient air is within this range:
Temperature	32 to 120°F
Humidity	10 to 90% RH (non condensing)

