Short circuit proof PCB transformer

AVB 0,35/2/18



Advantages

Minimum size at high output

Unconditionally short-circuit proof

Double input voltage for series or parallel connection

Also with double output voltage for series or parallel connection

Designed for high ambient temperatures

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDensiFill resin encapsulation

Coil shell in 2-chamber technology

Self-extinguishing potting and hood material

Applications

As a mains transformer for adjustment of the voltage and simple electrical isolation.

As a safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Circuit Diagram

PRI 1 SEC 1	PRI 1 SEC 1
PRI 2 SEC 2	
3 25	PRI 2 . SEC 2

Standards



Mains transformer to: VDE 0570 Teil 2-1, DIN EN 61558-2-1, EN 61558-2-1, IEC 61558-2-1, UL 5085-1/-2, CSA 22.2 No.66

Approvals



UL 5085-1/-2, CSA 22.2 No.66





Short circuit proof PCB transformer **AVB 0,35/2/18**

	Туре	AVB 0,35/2/18		Туре	AVB 0,35/2/18
Electrical data +	Input		0	Terminal and mounting Terminals	
		2 x 115 Vac	۳ <u>.</u>	Terminals	Pins for printed circuit boards
	Rated frequency	50 - 60 Hz		Pin (ø)	0.6
	Output		data	Measures and weights	
	Rated output voltage	2 x 18 Vac	9	Core type	EE 20/6,1
	Rated Power	0.35 VA	g	Weight	0.02 kg
	No-load voltage (app. x factor)	1.80	.ie		
	No-load loss (typ.)	1.30 W	<u>e</u>	 15.0 ►	
	Efficiency	30 %	Mechanical	15.0	
	Standards		ž		↑
	Classification	Mains transformer			22.0
	Approvals			15.0 PRI SEC	5.0
	Approvals	cURus			
	Environment				5.0
	Ambient temperature max.	70 °C		22.7 ▶	3.0
	Safety and protection				
	Туре	encapsulated			
	Class of Insulation System	VDE=B, UL=class 105			
	Protection index	IP 00			
	Safety class (prepared)	II			
	Short circuit strength	inherently short-circuit proof			
	Order numbers				
	Order Number	AVB 0,35/2/18			



