Short circuit proof PCB transformer

AVB 2,0/2/12



Advantages

Minimum size at high output

Unconditionally short-circuit proof

Double input voltage for series or parallel connection

Also with double output voltage for series or parallel connection

Designed for high ambient temperatures

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDensiFill resin encapsulation

Coil shell in 2-chamber technology

Self-extinguishing potting and hood material

Applications

As a mains transformer for adjustment of the voltage and simple electrical isolation.

As a safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Circuit Diagram

·	IС	°	5
PRI1 }	SEC 1	PRI 1.3	SEC 1
کــــ	۰	Ŭ	_
·			0
PRI2 3	SEC 2	~	
	\	PRI 2 . 3	SEC 2
	- —	<u></u>	

Standards



Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals



UL 5085-1/-2, CSA 22.2 No.66





Short circuit proof PCB transformer **AVB 2,0/2/12**

	Type	AVB 2,0/2/12		Туре
1+ ∫	Input		0	Terminal and mounting
	Rated input Voltage	2 x 115 Vac	30	Terminals
	Rated frequency	50 - 60 Hz		Pin (ø)
ta	Output		data	Measures and weights
Electrical data	Rated output voltage	2 x 12 Vac	9	Core type
-	Rated Power	2.00 VA	Mechanical	Weight
.은	No-load voltage (app. x factor)	1.43	.e	
당	No-load loss (typ.)	0.90 W	اق	20.0
e	Efficiency	0 %	20	20.0
	Standards		Š	
	Classification	Safety isolating transformer		nc ·
	Approvals			20.0 10.0 PRI SEC
	Approvals	cURus		<u> </u>
	Environment			<u> </u>
	Ambient temperature max.	70 °C		
	Safety and protection			27.3
	Туре	encapsulated		
	Class of Insulation System	VDE=B, UL=class 105		
	Protection index	IP 00		
	Safety class (prepared)			
	Short circuit strength	inherently short-circuit proof		
	Order numbers			
	Order Number	AVB 2,0/2/12		



