Short circuit proof low profile transformer

FLD 48/18



Advantages

Minimum size at high output

Low height

Integrated overload protection using PTC in the input

Double input voltage for series or parallel connection

Double output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDensiFill resin encapsulation

Coil shell in 2-chamber technology

Self-extinguishing potting material

Applications

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Circuit Diagram



Standards



Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6

Approvals



ENEC 10 (VDE)



Short circuit proof low profile transformer **FLD 48/18**

	Туре	FLD 48/18		Туре		FLD 48/18	
Electrical data 🕇 🦰	Input		0	Terminal and mounting Terminals FLD 48/18 Pins for printed circuit boards			
	Rated input Voltage	2 x 115 Vac		Terminals		Pins for printed circuit boards	
	Rated frequency	50 - 60 Hz		Measures and weights			
	Output		data	Core type		UI 48/26,0	
	Rated output voltage	2 x 18 Vac	ınical	Weight	1.02 kg		
	Rated Power	48.0 VA					
	No-load voltage (app. x factor)	1.20		27.0 PRI SEC	×1.0 17.0	37.0 10.0 60.0 70.0	
	No-load loss (typ.)	4.50 W					
	Efficiency	79 %			SEC 10.		
	Standards		Σ				
	Classification	Safety isolating transformer					
	Approvals						
	Approvals	ENEC 10 (VDE)			10 1		
	Environment						
	Ambient temperature max.	40 °C		86.5 ►			
	Safety and protection						
	Туре	encapsulated					
	Class of Insulation System	E					
	Protection index	IP 00					
	Safety class (prepared)	II .					
	Short circuit strength	non-inherently short-circuit proof					
	Order numbers						
	Order Number	FLD 48/18					