Short circuit proof PCB transformer

APT 7,5/2/15



Advantages

Minimum size at high output

Integrated overload protection using PTC in the input

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDensiFill resin encapsulation

Coil shell in 2-chamber technology

Self-extinguishing potting material

Space saving installation thanks to additional screw mounting in the base

Applications

As a safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because $% \left(1\right) =\left(1\right) \left(1\right) \left($ of the limit on the output voltage.

Standards



Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals





ENEC 10 (VDE), UL 5085-1/-2, CSA 22.2 No.66





Short circuit proof PCB transformer **APT 7,5/2/15**

	Туре	APT 7,5/2/15		Туре	APT 7,5/2/15
Electrical data 🛨	Input		0 1	Terminal and mounting	
	Rated input Voltage	115 Vac	30	Terminals	Pins for printed circuit boards
	Rated frequency	50 - 60 Hz		Measures and weights	
	Output		苕	Dimension (W x H x D)	_
	Rated output voltage	2 x 15 Vac	<u></u>	Pin (ø)	0.8 mm
	Rated Power	7.5 VA		Core type	El 48/16,8
	No-load voltage (app. x factor)	1.21		Weight	0.28 kg
	No-load loss (typ.)	1.30 W			
	Efficiency	65 %			
	Standards		Š		
	Classification	Safety isolating transformer			
	Approvals				
	Approvals	cURus, ENEC (VDE)			
	Environment				
	Ambient temperature max.	40 °C			
	Safety and protection				
	Туре	encapsulated			
	Class of Insulation System	VDE=B, UL=class 105			
	Protection index	IP 00			
	Safety class (prepared)	II			
	Short circuit strength	non-inherently short-circuit proof			
	Order numbers				
	Order Number	APT 7,5/2/15			