Waveform Generator DDS/ARB





Features:

| Channels | 2 | |
|------------------------|--|--|
| Sample Rate | 250MS/S | |
| Output Frequency | 60MHz | |
| Frequency Resolution | 1μHz | |
| Vertical Resolution | 14bits | |
| Max. Arb Memory Depth | 1Mpts | |
| Waveforms | Sine, Square, Ramp, Triangle, Pulse, Noise, DC, Arb | |
| Output Amplitude Range | 1mVpp to 10Vpp (50 Ω), 2mVpp to 20Vpp (1M Ω) | |
| Modulation Types | AM, FM, PM, ASK, FSK, PWM, SWEEP, BURST | |
| Interfaces | USB DEVICE, USB Host, LAN | |

General Characteristics:

| Power | 100-240V AC / 40-400Hz | |
|-----------------------------|---|--|
| Product Colour | White and Grey | |
| Product Net Weight | 3.2kgs | |
| Product Size | 231mm × 94mm × 283mm | |
| Standard Accessories | BNC to BNC Cable, Power Cord, USB CABLE, PC SOFTWARE CD | |
| Standard Individual Packing | 1pc Gift Box, English Manual | |

Part Number Table

| Description | | Part Number |
|-------------|-----------------------------|-------------|
| | Waveform Generator; DDS/ARB | 72-2500 |

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com www.cpc.co.uk www.mcmelectronics.com

