

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

Part Number: [03-09-2092](#)
Status: **Active**
Overview: [Standard .093" Pin and Socket Connectors](#)
Description: [2.36mm Diameter Standard .093" Pin and Socket Plug Housings, 9 Circuits, 3 Rows](#)

Documents:
[3D Model](#)
[Drawing \(PDF\)](#)
[Product Specification PS-02-09 \(PDF\)](#)
[Product Specification PS-1292-001 \(PDF\)](#)
[Product Specification PS-1292-002 \(PDF\)](#)
[Product Specification PS-43660-9999 \(PDF\)](#)
[RoHS Certificate of Compliance \(PDF\)](#)

Agency Certification

CSA LR19980
UL E29179

General

Product Family Crimp Housings
Series [1292](#)
Application Power, Wire-to-Wire
Comments 14.0A max. can be achieved when housing is used with 42477 or 42478 terminals
Overview [Standard .093" Pin and Socket Connectors](#)
Product Name Standard .093"
UPC 800753614888

Physical

Circuits (maximum) 9
Color - Resin Natural
Flammability 94V-2
Gender Plug
Glow-Wire Compliant No
Material - Resin Nylon
Net Weight 3.542/g
Number of Rows 3
Packaging Type Bag
Panel Mount No
Pitch - Mating Interface 5.03mm
Stackable No
Temperature Range - Operating -40°C to +105°C

Electrical


Current - Maximum per Contact 11A

Material Info

Old Part Number 1292-P1

Reference - Drawing Numbers

Product Specification PS-02-09, PS-1292-001, PS-1292-002, PS-43660-9999
Sales Drawing SD-1292-0001



Series

image - Reference only

EU RoHS
ELV and RoHS
Compliant
REACH SVHC
Contains SVHC: No
Low-Halogen Status
Low-Halogen

China RoHS



Need more information on product environmental compliance?
Email productcompliance@molex.com
For a multiple part number RoHS Certificate of Compliance, [click here](#)
Please visit the [Contact Us](#) section for any non-product compliance questions.

Search Parts in this Series
[1292Series](#)

Mates With
[03-09-1091](#) , [03-09-1092](#) , [03-09-1093](#) ,
[03-09-1094](#)

Use With
[1189](#) Crimp Terminals, [1190](#) Crimp Terminals, [1380](#) Male Crimp Terminals, [1381](#) Female Crimp Terminals, [1433](#) Crimp Terminals, [1434](#) Male Crimp Terminals, [1973](#) , [2151](#) , [2273](#) , [2870](#) , [2871](#) , [4272](#) , [4550](#) , [6271](#)