


C5 Series

0104.2 - Speaker, Transformer, Baffle and Universal Volume Control 0104.3 - Speaker, Transformer, Baffle 0104.3 - Speaker, Transformer

0104 - CEILING MOUNTED SPEAKER ASSEMBLIES





The Quam C5/xx/ Wx/x is a complete loudspeaker assembly, with 8" frame, 12W dual-cone loudspeaker, steel baffle as specified; transformer and volume control as specified. Finish: Baffle, white baked epoxy hybrid, Loudspeaker, black baked epoxy hybrid.

Loudspeaker Mounting Options:

Screw mount or welded stud mount

Transformer options: 25V, 70.7V or 25V/70.7V, pig-tail Volume Control, Universal- If specified: Screw / knob

INTENDED USE

All variants: Downward facing, ceiling mounted, Interior environment.

Program Material: Signal tones, voice and music

SYSTEM COMPONENTS

Loudspeaker	8C5PAX
Transformer Options	5 taps at -3 dB levels
25V, 4W	Order as C5/ <u>B25</u> /Wx/xx
70.7V, 4W	Order as C5/ <u>B70</u> /Wx/xx
25V/70.7V, 5W	Order as C5/ <u>BU</u> /Wx/xx
Baffle Options	
Screw Mount	Order as C5/xx/ <u>W</u> /xx
Stud Mount	Order as C5/xx/ <u>W</u> S/xx
Volume Control Option	Order as C5/xx/xx/ <u>VC</u>

RECOMMENDED ADDITIONAL QUAM COMPONENTS:

0401.1- Backboxes, Round

0402- Loudspeaker mounting devices

ADDITIONAL COMPONENT SUBSTITUTIONS AVAILABLEContact Factory

0104.6- Customer Specified Assembly

AUDIO SPECIFICATIONS

Speaker Size	8" frame
Average Sensitivity	92 dB-SPL, 1W/ 1M
Loudspeaker Power	12W-RMS, EIA 426A Standard
Rating	
Calculated Maximum	99 dB-SPL, 5W/ 1M
System Output	98 dB-SPL, 4W/ 1M
Magnet Type, Weight	BeFe Ceramic, 4.8 oz. Nominal
Frequency Response	65 Hz - 17 kHz
Nominal	90° Included Angle,
Coverage Angle	-6 dB / 2 kHz, Half space
Audio Connection	7" long, color-coded tinned wires
	pre-cut

Recommended construction sequences, installation instructions and A&E Specifications are available in various formats on the Quam Architects' and Engineers' Resources CD or on the web at: www.quamspeakers.com

Quam-Nichols Company 234 Fast Marguette Road (C

234 East Marquette Road, Chicago, IL 60637 Phone: (800) NEED NOW Fax: (888) NEED NOW (800) 633 - 3669 (888) 633 - 3669

E-Mail: neednow@qnc.com www.quamspeakers.com





© 2009 Quam-Nichols Company Quam-Nichols reserves the right to make changes and/or improvements to its products at any time and without notice.