ESD Safe Constant Temperature Controllable Premium Soldering Station





Overview

This is a premium smart digital soldering station. This product has been widely used in institutes, industrial production line, maintenance industry and other fields on the basis of sophisticated and practical product features

Applicable to

- Laboratories
- Production line
- Communication service maintenance
- Institutes
- Teaching and practice

Features

- · High definition LCD display, looks splendid
- · Quick temperature storing and retrieving to switch between frequently-used temperatures immediately
- Heater is manufactured by high-end temperature resistant material and through advanced process to obtain longer
 lifespan and save more
- · Digital temperature calibration enable easy operation
- · Temperatures read in Celsius or Fahrenheit
- · Compatible with international brand tips, convenient to choose tips

Specifications

: 60W	
: 220V AC ±10% 50Hz(110V AC 60Hz c	ptional)
: 150°C to 450°C (302°F to 842°F)	
: ±2°C (still air, no load)	
: ±15°C	
: <2Ω	
: <2mV	
: Buttons	
: Digital calibration	
: 60W dual-wire ceramic heater	
: (L)146mm × (W)120mm × (H)91mm	
: 1.8kg	
	: 220V AC ±10% 50Hz(110V AC 60Hz o : 150°C to 450°C (302°F to 842°F) : ±2°C (still air, no load) : ±15°C : <2Ω : <2mV : Buttons : Digital calibration : 60W dual-wire ceramic heater : (L)146mm × (W)120mm × (H)91mm

Part Number Table

Description	Part Number
Soldering Iron, 60W, 220V/110V	AT907-938D
Soldering Station, Digital, ESD, EU	21-10115 EU
Soldering Station, Digital, ESD, UK	21-10115 UK

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com www.cpc.co.uk www.mcmelectronics.com

