

## 2-Port Compact PS/2 KVM Switch w/Audio and Cable

MODEL NUMBER: **B004-VPA2-K-R**



### Description

The B004-VPA2-K-R is a 2-port Compact PS/2 KVM Switch with optional audio and microphone switching function. It allows you to access, control, boot and reboot two PS/2-enabled computers from a single console (keyboard, monitor and mouse). The independent audio/mic switching function allows an uninterrupted audio experience - you can continue listening to audio even when you switch to the other computer. Compatible with all major operating systems.

### Features

- Fast, easy switching via keyboard hot keys or push buttons
- Plug-and-play setup - no software required
- Hot-swap capability allows easy addition or removal of computers without powering down the switch or other computers
- Speaker and microphone connections allow sharing of audio components between systems (standard 3.5 mm audio connections)
- Independent audio switching allows you to listen to audio from one computer while switching to the other computer
- Supports video resolutions up to 2048 x 1536 (standard 15-pin VGA connectors)
- Supports Microsoft® IntelliMouse® and the scrolling wheel on most mice
- Compact design saves desk space
- Does not require an AC adapter
- Compatible with all major operating systems
- Includes two, 6ft Cable Kits

## Specifications

### Highlights

- Fast, easy switching via keyboard hot keys or push buttons
- Allows sharing of audio components between systems; listen to music from one computer while accessing another
- Compact design saves desk space
- No software or AC adapter required
- (x2) 6ft PS/2 KVM Cable kits and (x2) 6ft 3.5mm Audio Cable Kits included
- Compatible with all major operating systems

### Applications

- Use this KVM switch when accessing two PS/2-equipped computers with one monitor, keyboard and mouse.

### System Requirements

- Console: VGA, SVGA or Multisync Monitor, PS/2 Keyboard and PS/2 Mouse
- Computers: VGA, SVGA or Multisync Monitor Port, PS/2 Keyboard Port and PS/2 Mouse Port
- Audio (Optional): Speakers with standard 3.5mm Connectors and a computer with 3.5mm ports
- Compatible with all major operating systems

### Package Includes

- Compact 2-port PS/2 KVM Switch with Audio
- (2) 6ft PS/2 KVM Cable Kits and (2) 6ft 3.5mm Audio Cable Kits
- Owner's Manual with Warranty Information



<b>OVERVIEW</b>	
Users	1
Console	No
Max CPU	2
<b>PHYSICAL</b>	
Color	Black
LCD Monitor (in.)	Not Applicable
LCD Monitor (cm)	Not Applicable
<b>ENVIRONMENTAL</b>	
BTUs	17.065
<b>COMMUNICATIONS</b>	
Port Control	Push Buttons, Hotkeys
IP Remote Access	No
<b>CONNECTIONS</b>	
Ports	2
PC/Server Connections	PS/2; VGA
Included KVM Cable (Equipment Side) - Connector 1	HD15 (Male)
Included KVM Cable (Equipment Side) - Connector 2	(x2) MiniDIN6 (Male)
Included KVM Cable (Equipment Side) - Connector 3	(x2) 3.5mm (Male)
Local Console Ports - Port 1	HD15 (Female)
Local Console Ports - Port 2	(x2) MiniDIN6 (Female)
Local Console Ports - Port 3	(x2) 3.5mm (Female)
<b>SPECIAL FEATURES</b>	
Cat5 KVM Switch	No
<b>CERTIFICATIONS</b>	
Certifications	FCC, CE, RoHS Compliant



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

NIAP-Certified Secure	No
<b>WARRANTY</b>	
Product Warranty Period (Worldwide)	1-year limited warranty

© 2015 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.

Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<http://www.tripplite.com/products/product-certification-agencies>