

200MHz Passive Oscilloscope Probe



RoHS
Compliant



Description:

General purpose series 200MHz, 1x/10x switchable probe with additional REF switch position. The REF position grounds the input tip allowing for convenient trace leveling.
200MHz (-3 dB) bandwidth
High impedance input (10 M Ω /14 pF - 10x position)
10 – 35 pF compensation range
300V CAT II
REF switch position

Features:

- Snap-Locking Sprung Hook
- Easily replaceable tip
- Large accessory set
- Meets IEC 61010-031

Specifications:

Type	: 5mm Passive Voltage
Bandwidth	: 10/200MHz
Attenuation	: 1x/10x/REF
Input Impedance	: 1/10M Ω
Input Capacitance	: 90/14pF
Output Impedance	: 1M Ω
Risetime	: 35/1.8 ns
IEC Rating	: 300V CAT II
Compensation	: 10–35 pF
Length	: 1.2m
Operating Temperature	: 0° to +50°C
Humidity	: 85% RH or less (at 35°C)

Accessories included : 15 cm Ground Lead, Replacement Tip, Black Snap-on Sprung Hook, Tip Insulator, IC Tip, BNC Adapter, Probe Tip Ground, Trimmer Tool & Identifier Rings.

The High Performance family is a high quality, general purpose set of 5mm Passive Voltage Oscilloscope probes. They are excellent replacement probes for all makes and models of oscilloscopes.

Part Number Table

Description	Part Number
200MHz Passive Oscilloscope Probe	76-105

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

