



- Ground cord used to connect mats to (Earth Bonding Point) plugs
- One end terminated with female snap socket; other end with M5 ring terminal
- 1 megohm (1 x 10<sup>6</sup> ohms) current limiting resistor in socket end
- 2.5mm cord diameter
- PVC insulation with 7 ends duplex tinsel copper conductor

Item #	Description
VER-26972	CORD,STRAIGHT,0.7M,10MMSOCKET/ M5 RING TERMINAL

"EPA ground cords shall be used to make electrical connections between groundable points and the EPA ground facility.

Where a single resistor is used in the EPA ground cord, this shall be located near the groundable point. Where more than one resistor is used, a resistor of a minimum resistance value of one half the total resistance shall be located near the groundable point.

When accessible, the EPA ground cord and its groundable point connection shall be shrouded by insulating material." (EN 61340-5-1 section 5.3.4 EPA ground cords)

Vermason

Unless otherwise noted, tolerance is ±10% Specifications and procedures subject to change without notice.



VERMASON UNIT C, 4TH DIMENSION, FOURTH AVENUE, LETCHWORTH, HERTS, SG6 2TD UK PHONE: +44 (0) 1462-672005, FAX: +44 (0) 1462-670440 E-MAIL:<u>Service@Vermason.co.uk</u>, INTERNET: <u>Vermason.co.uk</u> Drawing Number VER-26972 DATE: September 2015

Made in the

United Kingdom