

SD Memory Card Connector multicomp



Features:

- Right angle surface mount terminal •
- 9 contacts
- Gold plating •
- Write protect and card detect indication ٠
- Maximum Mating Cycles: 10,000 •



www.element14.com www.farnell.com www.newark.com



1.775 1.825 13.700 1.450 8 99 1.400 2 3 - 1.300 Т ÐŒ 13.700 Switch #3 Switch #1 27.400 1.625 22.700 8 2.200 24.000 8 뒅 1.850 6 ភ្ល 3 - 1.400 ĝ Σ Ľ ğ 3 1.275 5 $2 - \phi 1.400$ 1.20 ± 0.05 **SD Card PIN Assignment** ¥ 0.08 В-С В 1.050 ف References 2.000 PIN Name 4.750 400 5.350 CD/DAT3 2.00 1 20 2.50 2.900 2 CMD/D1 17.50 Switch #2 3 VSS1 2.600 4 VDD 2.100 5 CLK/SCLK 1.975 VSS2 6 12.000 7 DAT0 13.500 8 DAT1 9 DAT2 26.800 Part Number Explanation: **SDBMF** 2 009 15 Β Ω **Contact Area Plating** Package Type Plating Type Contact Area Plating : 15 = 15µ Inches Gold Plating. Package Type : 0 = Tray. **Part Number Table** Plating Type : T = Lead Free. Description Part Number Card, SD, Push/Push SDBMF-00915B0T2 Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group as ware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com www.farnell.com www.newark.com

