

## Is Now Part of



# ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo



# FDC606P

# P-Channel 1.8V Specified PowerTrench® MOSFET

### **General Description**

This P-Channel 1.8V specified MOSFET uses Fairchild's low voltage PowerTrench process. It has been optimized for battery power management applications.

### **Applications**


- Battery management
- Load switch
- Battery protection


#### **Features**

• -6 A, -12 V.  $R_{DS(ON)} = 26 \text{ m}\Omega$  @  $V_{GS} = -4.5 \text{ V}$   $R_{DS(ON)} = 35 \text{ m}\Omega$  @  $V_{GS} = -2.5 \text{ V}$ 

 $R_{DS(ON)} = 53 \text{ m}\Omega$  @  $V_{GS} = -1.8 \text{ V}$ 

- · Fast switching speed
- High performance trench technology for extremely low  $R_{\mbox{\scriptsize DS(ON)}}$





## Absolute Maximum Ratings TA=25°C unless otherwise noted

Symbol	Parameter		Ratings	Units
V <sub>DSS</sub>	Drain-Source Voltage		-12	V
V <sub>GSS</sub>	Gate-Source Voltage		±8	V
I <sub>D</sub>	Drain Current - Continuous	(Note 1a)	-6	Α
	- Pulsed		-20	
P <sub>D</sub>	Maximum Power Dissipation	(Note 1a)	1.6	W
		(Note 1b)	0.8	
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range		-55 to +150	°C

## **Thermal Characteristics**

R <sub>θJA</sub>	Thermal Resistance, Junction-to-Ambient	(Note 1a)	78	°C/W
R <sub>eJC</sub>	Thermal Resistance, Junction-to-Case	(Note 1)	30	°C/W

**Package Marking and Ordering Information** 

Device Marking	Device	Reel Size	Tape width	Quantity	
.606	FDC606P	7"	8mm	3000 units	

Symbol	Parameter	Test Conditions	Min	Тур	Max	Units
Off Char	acteristics	1	II.	I.		I.
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	$V_{GS} = 0 \text{ V}, \qquad I_{D} = -250 \mu\text{A}$	-12			V
<u>ΔBV<sub>DSS</sub></u> ΔT <sub>J</sub>	Breakdown Voltage Temperature Coefficient	$I_D$ = -250 $\mu$ A,Referenced to 25°C		-3		mV/°C
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	$V_{DS} = -10 \text{ V},  V_{GS} = 0 \text{ V}$			<b>–</b> 1	μΑ
$I_{GSSF}$	Gate–Body Leakage, Forward	$V_{GS} = 8 \text{ V}, \qquad V_{DS} = 0 \text{ V}$			100	nA
I <sub>GSSR</sub>	Gate–Body Leakage, Reverse	$V_{GS} = -8 \text{ V}, \qquad V_{DS} = 0 \text{ V}$			-100	nA
On Char	acteristics (Note 2)					
$V_{GS(th)}$	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = -250 \mu A$	-0.4	-0.5	-1.5	V
$\Delta V_{GS(th)} \over \Delta T_J$	Gate Threshold Voltage Temperature Coefficient	$I_D$ = -250 $\mu$ A,Referenced to 25°C		2.5		mV/°C
R <sub>DS(on)</sub>	Static Drain–Source On–Resistance	$V_{GS} = -4.5 \text{ V},  I_D = -6 \text{ A}$ $V_{GS} = -2.5 \text{ V},  I_D = -5 \text{ A}$ $V_{GS} = -1.8 \text{ V},  I_D = -4 \text{ A}$ $V_{GS} = -4.5 \text{ V}, I_D = -6 \text{ A}, T_J = 125^{\circ}\text{C}$		21 26 34 28	26 35 53 35	mΩ
I <sub>D(on)</sub>	On-State Drain Current	$V_{GS} = -4.5 \text{ V}, \qquad V_{DS} = -5 \text{ V}$	-20			Α
<b>g</b> FS	Forward Transconductance	$V_{DS} = -5 \text{ V}, \qquad I_{D} = -6 \text{ A}$		25		S
Dynamio	Characteristics					
C <sub>iss</sub>	Input Capacitance	$V_{DS} = -6 \text{ V}, \qquad V_{GS} = 0 \text{ V},$		1699		pF
Coss	Output Capacitance	f = 1.0 MHz		679		pF
C <sub>rss</sub>	Reverse Transfer Capacitance			423		pF
Switchir	ng Characteristics (Note 2)					
t <sub>d(on)</sub>	Turn-On Delay Time	$V_{DD} = -6 \text{ V}, \qquad I_{D} = -1 \text{ A},$		11	19	ns
t <sub>r</sub>	Turn-On Rise Time	$V_{GS} = -4.5 \text{ V}, \qquad R_{GEN} = 6 \Omega$		10	20	ns
$t_{d(off)}$	Turn-Off Delay Time	1		89	142	ns
t <sub>f</sub>	Turn-Off Fall Time	1		70	112	ns
Qg	Total Gate Charge	$V_{DS} = -6 \text{ V}, \qquad I_{D} = -6 \text{ A},$		18	25	nC
Q <sub>gs</sub>	Gate-Source Charge	$V_{GS} = -4.5 \text{ V}$		3		nC
$Q_{gd}$	Gate-Drain Charge			4.2		nC
Drain-S	ource Diode Characteristics	and Maximum Ratings				
Is	Maximum Continuous Drain-Source				-1.3	Α
V <sub>SD</sub>	Drain–Source Diode Forward Voltage	$V_{GS} = 0 \text{ V},  I_S = -1.3 \text{ A}  \text{(Note 2)}$		-0.6	-1.2	V

#### Notes:

- 1.  $R_{\theta JA}$  is the sum of the junction-to-case and case-to-ambient resistance where the case thermal reference is defined as the solder mounting surface of the drain pins.  $R_{\theta JC}$  is guaranteed by design while  $R_{\theta CA}$  is determined by the user's board design.
- a. 78°C/W when mounted on a 1in² pad of 2oz copper on FR-4 board.
- b. 156°C/W when mounted on a minimum pad.
- 2. Pulse Test: Pulse Width  $\leq$  300  $\mu$ s, Duty Cycle  $\leq$  2.0%

## **Typical Characteristics**





Figure 1. On-Region Characteristics.



2.6

Figure 2. On-Resistance Variation with Drain Current and Gate Voltage.




Figure 3. On-Resistance Variation with Temperature.




Figure 4. On-Resistance Variation with Gate-to-Source Voltage.




Figure 5. Transfer Characteristics.





Figure 6. Body Diode Forward Voltage Variation with Source Current and Temperature.

## **Typical Characteristics**







Figure 7. Gate Charge Characteristics.








Figure 9. Maximum Safe Operating Area.






Figure 11. Transient Thermal Response Curve.

Thermal characterization performed using the conditions described in Note 1b. Transient thermal response will change depending on the circuit board design.

#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

SMART START™  $VCX^{TM}$ FAST ® OPTOLOGIC™ STAR\*POWER™ FASTr™ Bottomless™ OPTOPLANAR™ Stealth™ CoolFET™ FRFET™ PACMAN™ SuperSOT™-3 CROSSVOLT™ GlobalOptoisolator™ POP™ SuperSOT™-6 DenseTrench™ GTO™ Power247™  $HiSeC^{TM}$ SuperSOT™-8  $Power Trench^{\, @}$ DOME™ SyncFET™ EcoSPARK™ ISOPLANAR™ QFET™ TinyLogic™ E<sup>2</sup>CMOS<sup>TM</sup> LittleFET™  $OS^{TM}$ 

EnSigna™ MicroFET™ QT Optoelectronics™ TruTranslation™
FACT™ MicroPak™ Quiet Series™ UHC™
FACT Quiet Series™ MICROWIRE™ SILENT SWITCHER® UltraFET®

STAR\*POWER is used under license

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS. NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. H4