





LTR	ECO No.	REVISION	e pr	cke	nerat	ed 17.	20/2011 Page:
Α		ENGINEERING DRAWING	ww				6/30/98
В	5755	NEW PEI LOGO	J.O.				19 SEPT 00
С	6453	ADD KICK GUARD	C.L.		DK		06 AUG 01
D	7350	CORR TEXT TO MATCH CHASS	C.L.		J.O.		13 JAN 03
Е	8267	CORR. THERMAL BREAKER	LS		DK		07 FEB 06
F	013471	ADD GROUND SCREW	AD				09 JUL 10

NOTES:

 RACK MOUNTED STEEL CHASSIS, GOLD ZINC PLATED 19.00" WIDE STANDARD RACK MOUNTING 3.25" HIGH CHASSIS SUPPORT BRACKETS ARE REQUIRED

2. INPUT: 120/208 VAC 24A 3 PHASE WYE 50/60HZ. POWER CORD: 15 FOOT 10/5 SOOW CABLE WITH NEMA L21-30 PLUG

240 VAC 16A AT THREE NEMA L6-20 RECEPTACLES 120 VAC 16A AT EIGHT NEMA 5-20 RECEPTACLES (2 UNSWITCHED)

4. CIRCUIT BREAKERS: ONE 4-POLE 30A UL RECOGNIZED BREAKER, THREE 2-POLE 20A UL RECOGNIZED BREAKER ONE 1-POLE 20A RESETTABLE BREAKER

5. INDICATOR LIGHT: FOUR GREEN ONE ON WHEN MAIN BREAKER IS ON ONE FOR EACH SWITCHED SECTION

6. FILTER: EMI/RFI, 30 AMP RATING, COMMON MODE, LINE TO GROUND, NEUTRAL TO GROUND DIFFERENTIAL MODE, LINE TO LINE, LINE TO NEUTRAL

7. REMOTE: LATCHING WITH NORMALLY CLOSED EPO: 3 REMOTES, 1 SEQUENCE 3 PIN AMP CONNECTOR MATES WITH AMP # 1-480305-0 CONNECTOR WITH AMP # 60620-1 PINS.

REMOTE CONNECTOR

REM	ОТЕ	CONNECTOR	SAMPLE EPO/START REMOTE STATION				
PIN 1 PIN 2 PIN 3		START/ POWER ON EPO/ POWER OFF COMMON (NOT GROUND)	$\longleftarrow \bigcirc \bigcirc \bigcirc$	N.O. MOM CONTACT N.C. MAINT CONTACT (EPO COMMON (NOT GROUND)			

NOTE: LATCHING UNITS ARE DESIGNED FOR REMOTE OPERATION ONLY. EVEN WHEN THE "REMOTE/OFF/LOCAL" SWITCH IS SET TO "LOCAL" THE UNIT STILL REQUIRES A CLOSURE AT A REMOTE PORT

REMOTE START REQUIRES TWO CONDITIONS:

1) MAINTAINED CONTACT BETWEEN PINS 2 & 3

2) MOMENTARY CONTACT BETWEEN PINS 1 & 3

REMOTE EPO REQUIRES ONE CONDITION:

1) OPENING OF MAINTAINED CONTACT BETWEEN PINS 2 & 3 THIS WILL TURN OFF SWITCHED OUTLETS REGARDLESS OF REMOTE SWITCH POSITION.

FOR START UP OF ADDITIONAL LATCHING UNITS: CONNECT PINS 1 & 2 OF THE SEQUENCE PORT TO A REMOTE PORT ON ANOTHER LATCHING UNIT. DO NOT CONNECT TO ANOTHER SEQUENCE PORT.

8. SPIKE AND SURGE SUPPRESSION: NONE

9. MULTIPLE TIME DELAY:

4 SECONDS BETWEEN EACH SWITCHED SECTION SEQUENCE PORT ACTIVATES 4 SECONDS AFTER THE LAST SECTION TURNS ON.

10. U.L. RECOGNIZED PRODUCT

EATON APPROVAL

DATE

THE INFORMATION AND DESIGN DISCLOSED HEREIN WAS ORIGINATED BY AND IS THE PROPERTY OF EATON CORPORATION. EATON CORPORATION RESERVES ALL PATENT, PROPRIETARY, DESIGN, MANUFACTURING, REPRODUCTION, USE AND SALE RIGHTS THERETO, AND TO ANY ARTICLE DISCLOSED THEREIN, EXCEPT TO THE EXTENT

±.020 .XXX OTHERWISE ±.010 SPECIFIED

9650 Jeronimo Road. Irvine. California 92618 Phone (949) 452-9500 **ENGINEERING DIAGRAM FOR**

PC975-LT ASSY 3019

PC975-LT_3019_ME

NOT APPLY TO VENDOR PROPRIETARY PARTS. COPYRIGHT 2010 EATON CORP CAGE CODE 31795 3.4 D 1 OF 1