



# RP-SMA Straight Plug to U.FL

**RoHS  
Compliant**



## Specifications:

|                                 |                         |
|---------------------------------|-------------------------|
| Impedance                       | : 50Ω                   |
| Frequency Range                 | : DC to 3GHz            |
| Working Voltage                 | : 60 Vrms (Max.)        |
| Dielectric Withstanding Voltage | : 200Vrms (Min.)        |
| Insulation Resistance           | : 500MΩ (Min.)          |
| Connector Type A                | : U.FL Right Angle Plug |
| Connector Type B                | : RP-SMA Straight Plug  |
| Coaxial Cable Type              | : 1.37mm                |
| Cable Lengths                   | : 150mm                 |



Dimensions : Millimetres

| Item | Description   |
|------|---|
| 1    | RP-SMA B / H Jack for Ø1.37mm Cable (Nut × 1, Washer × 1) |
| 2    | Heat Shrink Tube F32 Ø2.5mm L = 15mm Colour : Black       |
| 3    | Ø1.37mm Cable Colour : Black                              |
| 4    | U.FL-LP-088 Shell for Ø1.37mm Cable                       |
| 5    | U.FL-LP-088 Terminal for Ø1.37mm Cable                    |

## Part Number Table

| Description  | Part Number    |
|--|----------------|
| RP-SMA Straight Plug to U.FL Right Angle Plug,<br>50Ω, 150mm | R-134G7210150C |

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.