
KEMET Part Number: T543X337M010AHW025



Tantalum, Polymer Tantalum, COTS, T543_COTS, 330 uF, 20%, 10 V, 7343, SMD, Polymer, Molded, COTS, Up Screening, N/A, 25 mOhms, Height Max = 4.3mm



| Dimensions | |
|------------|-----------------|
| Footprint | 7343 |
| L | 7.3mm +/-0.3mm |
| W | 4.3mm +/-0.3mm |
| Н | 4mm +/-0.3mm |
| Т | 0.13mm REF |
| S | 1.3mm +/-0.3mm |
| F | 2.4mm +/-0.1mm |
| Α | 3.8mm MIN |
| В | 0.5mm +/-0.15mm |
| E | 3.5mm REF |
| G | 3.5mm REF |
| Р | 1.7mm REF |
| R | 1mm REF |
| Х | 0.1mm +/-0.1mm |

| Packaging Specifications | | |
|--------------------------|------------|--|
| Weight: | 588.16 mg | |
| Packaging: | T&R, 178mm | |
| Packaging Quantity: | 500 | |

| General Information | | |
|---------------------|---|--|
| Dielectric: | Polymer Tantalum | |
| Style: | SMD Chip | |
| Series: | T543_COTS | |
| Description: | SMD, Polymer, Molded, COTS, Up Screening | |
| Features: | Non-Combustible, Up Screening, Low ESR, COTS | |
| RoHS: | No | |
| Termination: | Solder Coated | |
| Notes: | In polarity stripe, at KEMET's option, type may be indicated: no symbol = Standard (or low leakage) MnO2 tantalum chip, O = LowESR T494, R = Low ESR T495, F = Fused T496, HT = 150C rated T498 (or B45196P, B45198P), H = 175C rated T499, H2 = 200C rated T50 | |

| Specifications | |
|--------------------------|---|
| Capacitance: | 330 uF |
| Capacitance Tolerance: | 20% |
| Voltage DC: | 10 VDC (105C) |
| Temperature Range: | -55/+105C |
| Dissipation Factor: | 10% 120Hz 25C |
| Failure Rate: | N/A |
| Resistance: | 25 mOhms (100kHz) |
| Current: | 1116 mAmps (100kHz 45C) |
| Leakage Current: | 330 uAmps (5min 25C) |
| Testing and Reliability: | 10 Cycles Surge Current Testing At -55C And +85C |



Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.