Product datasheet Characteristics

ZB5AW713

white Ø40 illum mushroom pushbutton head Ø22 latching for integral LED



Main

Main					
Range of product	Harmony XB5				
Product or component type	Head for illuminated push-button				
Device short name	ZB5				
Product compatibility	Integral LED				
Bezel material	Plastic				
Mounting diameter	22 mm				
Sale per indivisible quantity	1				
Shape of signaling unit head	Round				
Shape of signaling unit head					
	Latching				
Type of operator	Latching Turn to release				
Type of operator Reset Operator profile					
Type of operator Reset	Turn to release				
Type of operator Reset Operator profile Complementary CAD overall width	Turn to release White mushroom Ø 40 mm unmarked				
Type of operator Reset Operator profile Complementary	Turn to release White mushroom Ø 40 mm unmarked 40 mm				
Type of operator Reset Operator profile Complementary CAD overall width CAD overall height	Turn to release White mushroom Ø 40 mm unmarked 40 mm 40 mm				
Type of operator Reset Operator profile Complementary CAD overall width CAD overall height CAD overall depth Product weight	Turn to release White mushroom Ø 40 mm unmarked 40 mm 40 mm 50 mm				
Type of operator Reset Operator profile Complementary CAD overall width CAD overall height CAD overall depth	Turn to release White mushroom Ø 40 mm unmarked 40 mm 40 mm 50 mm 0.022 kg				
Type of operator Reset Operator profile Complementary CAD overall width CAD overall height CAD overall depth Product weight Resistance to high pressure washer	Turn to release White mushroom Ø 40 mm unmarked 40 mm 40 mm 50 mm 0.022 kg 7000000 Pa at 55 °C,distance: 0.1 m				

Complementary

CAD overall width	40 mm
CAD overall height	40 mm
CAD overall depth	50 mm
Product weight	0.022 kg
Resistance to high pressure washer	7000000 Pa at 55 °C,distance: 0.1 m
Mechanical durability	300000 cycles
Station name	XALD 1 cut-out XALK 1 cut-out
Electrical composition code	M10 for <= 2 contacts using single blocks in front mounting with integral LED M6 for <= 2 contacts using single blocks in front mounting with integral LED and transformer MF1 for <= 2 contacts using single blocks in front mounting with integral LED MR1 for <= 2 contacts using single blocks in rear mounting with integral LED M3 for <= 4 contacts using single blocks in front mounting with integral LED M4 for <= 4 contacts using single and double blocks in front mounting with integral LED

Environment

Linnonnent				
Protective treatment	TC			
Ambient air temperature for storage	-4070 °C			
Ambient air temperature for operation	-4070 °C			
Overvoltage category	Class II conforming to IEC 60536			
Class of protection against electric shock	Class II conforming to IEC 60536			
IP degree of protection	IP69 IP66 conforming to IEC 60529 IP69K			
NEMA degree of protection	NEMA 13 NEMA 4X			
IK degree of protection	IK05 conforming to EN 50102			
Standards	GB 14048.5 EN/IEC 60947-1 UL 508 CSA C22.2 No 14 EN/IEC 60947-5-4 JIS C 4520 EN/IEC 60947-5-1			
Product certifications	BV UL listed GL RINA LROS (Lloyds register of shipping) DNV CSA			
Vibration resistance	5 gn (f = 2500 Hz) conforming to IEC 60068-2-6			
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27 50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27			

Contractual warranty


Warranty period

18 months

Product datasheet Dimensions Drawings

ZB5AW713


Dimensions



ZB5AW713

Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- Diameter on finished panel or support (1)
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended. \emptyset 22.5 mm recommended (\emptyset 22.3 $_0^{+0.4}$) / \emptyset 0.89 in. recommended (\emptyset 0.88 in. $_0^{+0.016}$) (2)
- (3)

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18

Detail of Lug Recess




- Diameter on finished panel or support (1)
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5AZ902 is recommended. \emptyset 22.5 mm recommended (\emptyset 22.3 $_0^{+0.4}$) / \emptyset 0.89 in. recommended (\emptyset 0.88 in. $_0^{+0.016}$) (2)
- (3)

ZB5AW713

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection


Panel Cut-outs (Viewed from Installer's Side)




- A: 30 mm min. / 1.18 in. min.
- B: 40 mm min. / 1.57 in. min.

Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

Dimensions in mm



B: 40 mm min.



B: 1.57 in. min.


General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB5AZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB5AZ079 fixing collar/pillar and its fixing screws:
 - every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
 - $^{\circ}$ with each selector switch head (ZB5AD•, ZB5AJ•, ZB5AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.




- (1) Head ZB5AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

Mounting of Adapter (Socket) ZBZ01•

- 1 2 elongated holes for ZBZ006 screw access
- + 2 1 hole Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 for centring adapter ZBZ01+
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ01•

Dimensions An + 18.1 relate to the Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 holes for centring adapter ZBZ01•.

Electrical Composition Corresponding to Code M3



Electrical Composition Corresponding to Code M4



Electrical Composition Corresponding to Codes M6 and P2



Electrical Composition Corresponding to Codes M5, M10, MF1, MR1 and MF2



Product datasheet **Technical Description**

Legend Single contact Double contact Light block 8 Possible location 4