# Product datasheet Characteristics

## XCKJ167H29

limit switch XCKJ - steel roller plunger reinforced - 1NC+1NO - snap - M20



#### Main

Mairi		
Range of product	OsiSense XC	
Series name	Standard format	-
Product or component type	Limit switch	
Device short name	XCKJ	
Sensor design	Form C conforming to CENELEC EN 50041	
Body type	Fixed	
Head type	Plunger head	<u>.</u>
Material	Metal	
Body material	Zamak	
Head material	Zamak	
Fixing mode	By the body	† •
Movement of operating head	Linear	<u> </u>
Type of operator	Spring return roller plunger metal (reinforced)	
Type of approach	Lateral approach 2 directions	
Cable entry	1 entry tapped for M20 x 1.5 cable gland, cable outer diameter: 713 mm	2.
Number of poles	2	
Contacts type and composition	1 NC + 1 NO	
Contacts operation	Snap action	

### Complementary

Switch actuation	By 30° cam	
Electrical connection	Screw-clamp terminals, clamping capacity: 1 x 0.342 x 1.5 mm²	
Contacts insulation form	Zb	
Number of steps	1	
Positive opening	With	
Positive opening minimum force	40 N	·
Minimum force for tripping	16 N	

Maximum actuation speed	1 m/s
[le] rated operational current	3 A at 240 V, AC-15, A300 conforming to EN/IEC 60947-5-1 appendix A 0.27 A at 250 V, DC-13, Q300 conforming to EN/IEC 60947-5-1 appendix A
[Ithe] conventional enclosed thermal current	10 A
[Ui] rated insulation voltage	300 V conforming to CSA C22.2 No 14 500 V degree of pollution 3 conforming to IEC 60947-1 300 V conforming to UL 508
Resistance across terminals	<= 25 MOhm conforming to IEC 60255-7 category 3
[Uimp] rated impulse withstand voltage	6 kV conforming to IEC 60664 6 kV conforming to IEC 60947-1
Short circuit protection	10 A by gG cartridge fuse
Electrical durability	5000000 cycles, DC-13, inductive load type, 24 V, 10 W, operating rate: <= 60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C 5000000 cycles, DC-13, inductive load type, 48 V, 7 W, operating rate: <= 60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C 5000000 cycles, DC-13, inductive load type, 120 V, 4 W, operating rate: <= 60 cyc/mn, load factor: 0.5 conforming to IEC 60947-5-1 appendix C
Mechanical durability	25000000 cycles
Width	40 mm
Height	77 mm
Depth	44 mm
Product weight	0.455 kg
Terminals description ISO n°1	(13-14)NO (21-22)NC

#### Environment

LITTION			
Shock resistance	50 gn (duration = 11 ms) conforming to IEC 60068-2-27		
Vibration resistance	25 gn (f = 10500 Hz) conforming to IEC 60068-2-6		
IP degree of protection	IP66 conforming to IEC 60529		
IK degree of protection	IK07 conforming to EN 50102		
Overvoltage category	Class I conforming to NF C 20-030 Class I conforming to IEC 61140		
Ambient air temperature for operation	-2570 °C		
Ambient air temperature for storage	-4070 °C		
Protective treatment	TC		
Product certifications	CCC CSA UL		
Standards	EN 60204-1 IEC 60204-1 EN 60947-5-1 CENELEC EN 50041 CSA C22.2 No 14 IEC 60947-5-1 UL 508		

### Offer Sustainability

Sustainable offer status	Green Premium product	
RoHS (date code: YYWW)	Compliant - since 0951 - Schneider Electric declaration of conformity	
	Schneider Electric declaration of conformity	
REACh	Reference not containing SVHC above the threshold	
	Reference not containing SVHC above the threshold	
Product end of life instructions	Need no specific recycling operations	


#### Contractual warranty

Warranty period	18 months	

# Product datasheet Dimensions Drawings

## XCKJ167H29

#### **Dimensions**




(1) 1 tapped entry M20 x 1.5

# Product datasheet Mounting and Clearance

## XCKJ167H29

### Mounting with Cable Entry

### Position of Cable Gland



- (1) Recommended
- (2) To be avoided

# Product datasheet Connections and Schema

# XCKJ167H29

### Wiring Diagram

2-pole NC + NO Snap Action

# Product datasheet Technical Description

## **XCKJ167H29**


**Characteristics of Actuation** 

Switch Actuation by 30° Cam



## XCKJ167H29

### Functionnal Diagram



- Positive opening point
- (A) Cam displacement
- (1) (2) (3) NC contact with positive opening operation
- Closed
- Open
- . Tripping
- (4) (5) Resetting