Product datasheet Characteristics

ZARC01

Charger for remote device



Main

		0
Range of product	Harmony XAR	necifi
Accessory / separate part type	Battery charger	for s
Accessory / separate part category	Electrical accessory	——ducts

Complementary

[Us] rated supply voltage 100240 V AC	
Network frequency 5060 Hz	:
Nominal output current 0.9 A at 90 V AC	
Connections - terminals 5-position plug-in connector	:
Product weight 0.26 kg	

Environment

Ambient air temperature for operation	> 040 °C	
Ambient air temperature for storage	> -2060 °C	_ 4

Offer Sustainability

•		<u>_</u>
Sustainable offer status	Not Green Premium product	و ع
RoHS (date code: YYWW)	Compliant - since 1415 - Schneider Electric declaration of conformity	
	Schneider Electric declaration of conformity	ส <u>ข</u>
REACh	Reference not containing SVHC above the threshold	
	Reference not containing SVHC above the threshold	