Digital Clamp Meter





General Characteristics

Power : AAA 1.5V × 3 LCD Size : 38mm × 24mm Product Colour : Yellow and Orange

Product Net Weight : 280g

Product Size : 220mm × 75mm × 40mm
Standard Accessories : Batteries, Test Lead
Safety Rating : CAT II 1000V
CAT III 600V

Specifications:

Basic Functions	Range	Best Accuracy	
AC Current (A)	6A/60A/600A	± (2.5%+5)	
AC Voltage (V)	6V/60V/600V/750V	± (1.2%+5)	
DC Voltage (V)	600mV/6V/60V/600V/1000V)V ± (0.8%+1)	
Resistance (Ω)	600Ω/6kΩ/60kΩ/600kΩ/6ΜΩ/60ΜΩ	DMΩ ± (1%+2)	
Capacitance	99.99nF/999.9nF/9.999µF/99.99µF/999.9µF/9.999mF/59.99mF	± (4%+5)	
Special Functions			
Display Count		6000	
Auto Range		$\sqrt{}$	
Jaw Capacity		30mm	
True RMS		$\sqrt{}$	
Diode	Around 3V	√	
NCV		√	
Auto Power Off	Around 15 Minutes	√	
Continuity Buzzer		√	
Low Battery Indication	≤3.6V	√	
Data Hold		√	
Relative Mode		√	
MAX/MIN		\checkmark	
LCD Backlight		\checkmark	
Flashlight		√	
Input Protection		√	
Input Impedance for DCV	≥10MΩ	√	

Part Number Table

Description		Part Number
	600A True RMS Digital Clamp Meter	72-3097

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com www.cpc.co.uk www.mcmelectronics.com

