

FUSEBLOCKS, HOLDERS AND ACCESSORIES



Catalog Number BM Series

CLASS M SUPPLEMENTARY FUSEBLOCKS:

BM Series: For use with any 13/32" x 1-1/2" Fuses (Edison MCL, MEQ, MEN, and MOL)

Construction: Thermoplastic, UL Flammability; 94VO

Ratings: 600 Volts AC, 30 Amps


Agency Approvals:

UL Recognized, Guide IZLT2, File E14853 CSA, Class 6225-01, File 47235

Catalog Data (600V)

		Terminal Type					
		Screw with					
		Quick	Pressure Plate w/	Box	Fig.		
Amps	Poles	Connect	Quick Connect	Lug	No.		
1/10	1	BM6031SQ	BM6031PQ	BM6031B	1		
to	2	BM6032SQ	BM6032PQ	BM6032B	2		
30	3	BM6033SQ	BM6033PQ	BM6033B	3		

Dimensional Data



CROSS REFERENCE								
NEW	OLD							
EDISON	EDISON	BUSSMANN	GOULD	LITTELFUSE				
BM6031SQ	EM631-33	BM6031SQ	30311	L60030M-1SQ				
BM6032SQ	EM632-33	BM6032SQ	30312	L60030M-2SQ				
BM6033SQ	EM633-33	BM6033SQ	30313	L60030M-3SQ				
BM6031PQ	EM631-44	BM6031PQ	30321	L60030M-1PQ				
BM6032PQ	EM632-44	BM6032PQ	30322	L60030M-2PQ				
BM6033PQ	EM633-44	BM6033PQ	30323	L60030M-3PQ				
BM6031B	EM631-11	BM6031B	30351	L60030M-1B				
BM6032B	EM632-11	BM6032B	30352	L60030M-2B				
BM6033B	EM633-11	BM6033B	30353	L60030M-3B				



Adapter for DIN and American Rails

FEATURES:

- Edison DIN-Rail Adapters permit secure, positive snap-on mounting of Edison 0 to 30 ampere fuseblocks (one, two, or three pole) on various size rails. (Rail mounting eliminates costly and time consuming drilling, tapping, and screw mounting.)
- Molded from "Lexan™ 141". . .a very high strength but flexible material.
- Adapter mechanically locks into mounting hole of fuseblock in seconds to become an integral part of the block.
- One adapter is required for Edison one and two pole blocks. Two adapters are required for three pole blocks.
- With the exception of the 32mm DIN-rail, all blocks with adapters can be removed from a rail simply by pulling up its release tab.
- Use of rail end-stops on both sides of adapters is recommended.

Adapter Catalog Data (For 0-30 Ampere Fuseblocks)

Fuseblock		Rails	Adapter	
Class	Туре	Size	Color	Cat. No.
CC		15mm (Symm.)		
G	DIN	32mm (Asymm.)	Black	DRA-1
*H (250V)		35mm (Symm.)		
*R (250)	American	17/64" (Symm.)	Cross	DRA-2
M Type	American	(also 35mm DIN)	Gray	

Package Quantities: Standard - 10; Bulk - 100 (Cat. No. BK/DRA-1 or BK/DRA-1.) *Mounting on 15mm rails is not recommended.

NOTE: New model Edison fuseblocks have elongated block-to-adapter mounting holes (old style fuseblocks will not accept the rail adapters).