XVPC09BW 50MM SOUNDER UNIT/0FF-WHITE RING/24 V



Main

Range of product	Harmony XVP Universal
Product or component type	Indicator bank
Beacon or indicator bank unit type	Audible unit
Mounting diameter	50 mm
Component name	XVPC
Noise level	5585 dB at 1 m
[Us] rated supply voltage	24 V DC
Housing colour	Cream

Complementary

Complementary		
Signalling type	Continuous or intermittent buzzer	
Assembly style	Customer assembly, up to 5 units	
Connections - terminals	Screw clamp terminals: 1 x 1.5 mm² with cable end	
Marking	CE	
[Ui] rated insulation voltage	250 V conforming to IEC 60947-1	
Nominal voltage limit	0.851.1 Un conforming to IEC 60947-5-1	
Current consumption	<= 15 mA	
[Uimp] rated impulse withstand voltage	4 kV conforming to IEC 60947-1	
Fundamental frequency	10 adjustable levels	<u>.s.</u>
CAD overall width	56 mm	
CAD overall height	129 mm	
CAD overall depth	56 mm	<u>.</u>
Product weight	0.153 kg	
		ā

Environment

Product certifications	CULus	
Standards	EN/IEC 60947-5-1	
Protective treatment	TC	
Ambient air temperature for storage	-4070 °C	
Ambient air temperature for operation	-2550 °C	
Electrical shock protection class	Class I on support tube conforming to IEC 61140	

Class II on base unit conforming to IEC 61140


IP degree of protection	IP43 conforming to IEC 60529	
Contractual warranty		
Warranty period	18 months	

XVPC09BW

Indicator Bank with Audible Unit

Dimensions

Below drawing shows an indicator bank with 1 audible stage and 1 illuminated stage. Select the number of stages according to the product characteristics in order to get b dimension.



Number of illuminated units	+ Audible	b in mm	b in in.
0	+ 1	129	5.08
1	+ 1	194	7.64
2	+ 1	256	10.08
3	+ 1	318	12.52
4	+ 1	380	14.96

Product data sheet Technical Description

XVPC09BW

Indicator Bank

Adjustment of Audible Signal for Buzzer



- Volume adjustment potentiometer: 55...85 dB. Use either across headed or flat tipped screwdriver.
- 2 Adjustment of type of audible signal according to position of 2 links. Use flat-nose pliers.

10 configurations are possible:

Conf.	Position of linl	ks and type of audible signal
1	5	1000 800 -0.25 0.25 s
2	5 \(\overline{\text{0}} \) \(\overline{\text{0}} \) \(\overline{\text{0}} \) \(\overline{\text{0}} \) \(\overline{\text{2}} \)	1200 500
3	5	1200 500 s
4	5	Hz 544 440 8 0,1
5	5	Hz
6	5	0 01)))))
7	5 0 6 0 0 0 1 0 2	1000 800 <u>Q.14</u> s
8	5	2400
9	5 () 6 () () 1 () () 2	Hz 420 0.625 0.625 s

Conf.	Position of links and type of audible signal
10	5 O 6 Hz 1200 500 500 500 500 5 5