

# RF Cable Assembly

## MCX Plug with RG174 Cable



RoHS  
Compliant




### Description

This MCX cable is a 0.9m RF174 coaxial cable assembly with one side MCX straight plug and other side is open. MCX RF coaxial connectors have the advantages of small, light, high reliability and superior performances. MCX connectors are widely used in the field where space is specially required.

### Specifications

Impedance	: 50Ω
Frequency	: 0-6GHz
Max. Working Voltage	: 250V
Insulation Resistance	: ≥1000MΩ
Dielectric Withstanding Voltage	: 750V
Body	: Brass Gold Plated
Centre Contact	: Brass Gold Plated
Insulator	: PTFE

### Diagram



No.	Description
1	MCX Connector
2	Heat Shrink Tube Ø5mm L=20mm Colour: Brown
3	RG174 Cable Colour : Brown

### Part Number Table

Description	Part Number
RF Cable Assembly, MCX Plug with RG174 Cable, 900mm, 50Ω, 0-6GHz	MC002114

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com  
www.farnell.com  
www.newark.com

