# **RF Coaxial Connector** BNC Jack for RG316, RG174 Cable Multicomp





## RoHS **Compliant**


#### **Description**

BNC connectors features a two stud, bayonet coupling which is engaged by rotating the sleeve less than ½ turn. BNC connectors are recommended for use at frequency up to 4GHz where repeated coupling and uncoupling are anticipate.

### **Specifications**

Impedance : 50Ω Frequency : 0-4GHz Working Voltage : 500V Max. Insulation Resistance : ≥5000MΩ Dielectric Withstanding Voltage: 1500V

#### Diagram



Dimensions	:	Millimetres

No.	Description	Material	Plated	Qty.
1	Centre Contact	QSnCu	Gold	
2	Body	Brass	Nickel	
3	Insulator	PTFE	-	1
4	irisulatoi	FIFE		
5	Bush	Brass		
6	Dusii	ыазэ		
7	Gasket	QSnCu	Nickel	
8	Nut	Brass		
9	ivut	DIdSS		

#### **Part Number Table**

Description	Part Number	
RF Coaxial Connector, BNC Jack, RG316/RG174 Cables, 50Ω, 0-4GHz	MC002131	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

