

Terminator: feed-through, 1 GHz 50 Ω 1 W BNC (m-f)



The TA051 feed-through attenuator is a coaxial terminator with BNC connectors. It is useful for connecting signals from 50 Ω sources into instruments with 1 MΩ impedance inputs, such as oscilloscopes.

TA051 Feed-through terminator specifications	
Bandwidth	DC to 1 GHz
Maximum power dissipation	1 W
Input impedance	50 Ω
Resistance tolerance	± 2%
Dimensions	56 x 20 x 17 mm (approximately 2.2 x 0.8 x 0.7 in)
Connectors	BNC, 1 male + 1 female
Construction	Shielded inner box with plastic shell
Weight	24 g (approximately 0.85 oz) each