

Product data sheet

Characteristics

NSYCCOHYT230VID

Climasys CC - electronic hygrotherm - 200...
240 V - temp -40...80°C - Hr 20...80%



Main

| | |
|---------------------------|---|
| Range | ClimaSys |
| Product name | ClimaSys CC |
| Product or component-type | Electronic hygrotherm |
| Temperature setting range | -40...80 °C |
| Humidity setting range | 20...80 % |
| Display type | OLED screen |
| Information displayed | Relative humidity Temperature in °C Temperature in °F |

Complementary

| | |
|---------------------------------------|---|
| Input voltage | 200...240 V AC |
| Sensor type | Optional NTC external sensor |
| Maximum switching capacity | 4 A 230 V AC |
| Electrical connection | 8 connectors 2.5 mm ² |
| Mounting mode | By screws Clipped |
| Height | External : 85 mm |
| Width | External : 56 mm |
| Depth | External : 44 mm |
| Mounting location | On mounting plate 35 mm DIN rail Spacial upright Cross rails |
| Ambient air temperature for operation | -40...80 °C |
| Hysteresis | 2 K programmed value |
| Hysteresis | 3 % |
| Number of outputs | 2 output(s) ventilation/heating function |
| Material | PC |
| Colour | Light grey |
| Flame retardance | Self-extinguishing conforming to UL94 (material V0) |
| Product certifications | UR |

Offer Sustainability

| | |
|------------------------|--|
| RoHS (date code: YYWW) | Compliant - since 0940 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Product Life Status : **Commercialised**

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.