




TRIAx

connecting the future



TRIAx 110 - TV/SAT combiner (diecast)

Article number: 340110

Product description:

TRIAx 110 - TV/SAT diecast combiner

TV/SAT mast combiners with F-connector in time-saving housing. The majority of our filters and combiners, are in the same type of time-saving housing as our mast amplifiers.

Specifications

ORDER INFORMATION	
EAN Number	5702663401105
CHARACTERISTICS	
Type.	Combiner
FREQUENCY	
Input 1 - band	SAT
Input 1 - channels	IF
Input 1 - frequency	950...2400 MHz
Input 2 - band	VHF/UHF
Input 2 - channels	2...69
Input 2 - frequency	47...862 MHz

LOSS	
Input 1 - through loss	2.0/3.0 dB
Input 1 - Stop Band Attenuation	22/25 dB
Input 2 - through loss	2.0 dB
Input 2 - Stop Band Attenuation	20 dB
OPERATIONAL	
DC Passthrough	Yes SAT
CONNECTORS	
Connector Type	F-female
Number of inputs	2
Number of outputs	1
MECHANICAL	
Product Height	38 mm
Product Depth	16 mm
Product Width	75 mm
Packaging Height	0,020 m
Packaging Width	0,060 m
Packaging Depth	0,050 m
Net Weight	0,045 kg
Tara Weight	0,006 kg
Total Weight	0,051 kg
Remarks	Diecast housing. DC throughpower to SAT input