# **HDMI Cable Tester**





## RoHS Compliant

#### **Features**

- Checks disorder, short, open & cross status of HDMI cables
- · Mapping continuity & proper configuration
- 19 pins & grounded connection
- 4 Status display LEDs
- · Capable of checking wiremap only with master unit
- · Designed with loopback function

### **Specifications**

Port Type : HDMI – A/C
Tracking Type : HDMI Cable
Testing Type : HDMI Cable

Power : 9V Alkaline Battery (Not Included)

Certificates : CE / REACH Warranty : 1 Year

#### **Technical Indexes**

HDMI cables with type A & C connectors conforming to 1.0,1.1,1.2,12a,1.3,1.3a,1.3b,1.4,1.4a,Category 1 and category 2 HDMI cables
19 Pin to Pin Wiremap and Shielding Detection
HDMI (Type A) × 2, Mini HDMI (Type A) × 1
Fast / Slow Scan / Step by Step
Under 50 meters
19 LEDs and Shield LED on both Master and Remote Unit
4 LEDs (Pass, Open, Short, Cross)
Yes
6V
DC 9V (NEDA 1604/ 6F22) × 1 (Not Included)
Operating: 0°C to 40°C < 80% RH
Storage: -10°C to 50°C <70%RH
Master Unit: 103mm × 66mm × 27mm
Remote Unit: 103mm × 35mm × 27mm

www.element14.com www.farnell.com www.newark.com www.cpc.co.uk



### **HDMI Cable Tester**



#### **Attention**

- · Read the user manual before use it
- · Do not connect high voltage lines to avoid burning out the machine
- Place the device in right place to avoid hurting others
- · Connect the cable to the right port

#### **Part Number Table**

Description	Part Number
HDMI Cable Tester, Type A/C Port	72-2970

Important Notice: This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com www.cpc.co.uk

