

Specification VT4 Voltage Tester



### Electrical

Maximum voltage: 1000V AC rms

Voltage sensitivity ranges: 12 to 1000V AC rms

50 to 1000V AC rms (default range) Frequency range: 50 to 400Hz

# Environmental

Temperature & Humidity (Operating & Storage):

 $0^{\circ}$ C to  $40^{\circ}$ C  $\leq 80\%$  R.H. Altitude: up to 2000m Pollution degree 2

## General

Power: 2 x 1.5V, AAA alkaline batteries (IEC LR03,

NEDA 24A)

Battery consumption: 80mA approx. Dimensions: 155(L) x 23(W) x 25(D) mm

Weight: 55g approx.

Includes: 2 x 1.5V AAA batteries, instructions

# Safety

Conforms to BS EN61010-1:2010 CAT IV 1000 V Class II, Double insulation IP rating: IP64 to BSEN 60529

#### **EMC**

Conforms to BS EN61326-1

Check out what else you can get from Martindale:

- 18th Edition Testers
- Accessories
- Calibration Equipment
- Continuity Testers
- Electricians' Kits
- Environmental Products
- Full Calibration & Repair Service
- Fuse Finders
- Digital Clamp Meters
- Digital Multimeters
- Labels
- Microwave Leakage Detectors
- Motor Maintenance Equipment
- Multifunction Testers
- Non-trip Loop Testers
- Pat Testers & Accessories
- Phase Rotation Testers
- Proving Units
- Socket Testers
- Thermometers & Probes
- Test Leads
- Voltage Indicators
- Specialist Metrohm Testers (4 & 5kV)
- Specialist Drummond Testers



Martindale Electric Company Limited Metrohm House, Imperial Park, Imperial Way, Watford, Hertfordshire, WD24 4PP, UK Tel: +44(0)1923 441717 Fax: +44 (0)1923 446900

E-mail:sales@martindale-electric.co.uk Website: www.martindale-electric.co.uk

© 2014 Martindale Electric Company Ltd. Registered in England No. 3387451. E. & O.E. LITVT4 Document Rev2