

Straight 3P XLR MIC Socket with Metal Cap


pro-SIGNAL



Specifications

Gender	: Socket
No. of Poles	: 3P
Mounting Type	: Cable
External Diameter	: 18.5mm
Boot Colour	: Black
Ring Colour	: Black

Diagram



Dimensions : Millimetres

Material Specifications

No.	Description	Material	Plating
1	Die-Cast Shell	Zinc Alloy (ZZnAL4-1)	Nickel
2	Insulator	PBT	Black
3	Seal	Rubber	Black
4	Latch	Stainless Steel	Tin
5	Push Button	Zinc Alloy (ZZnAL4-1)	Nickel
6	Female Pin	Phosphor Bronze	Silver
7	Ring Colour	ABS	Black
8	CAP	Zinc Alloy (ZZnAL4-1)	Nickel
9	Chuck	PA	Black
10	T-Ring	PP	-
11	Boot	PVC	Black

Part Number Table

Description	Part Number
Straight 3P XLR MIC Socket with Metal Cap, Cable, Zinc Alloy/ Nickel, Black	PS000231

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com
 www.farnell.com
 www.newark.com
 www.cpc.co.uk

pro-SIGNAL