Straight SMA 2-Hole Flange Mount Field Jack Receptacle

multicomp



Specifications

Connector Body Style Connector Mounting

- : Straight Field Jack Receptacle
- : 2-Hole Flange Mount

Electrical Specifications

Frequency Range Nominal Impedance Voltage Rating VSWR : DC 26.5GHz

- : 50Ω
- : 335V Max.
- : 1.17 Max. @ 18GHz / 1.21 Max. @ 26.5GHz

Material Specifications

| Bodies | : Stainless Steel per JIS SUS-303 |
|----------------|---------------------------------------------|
| Centre Contact | : Beryllium Copper per ASTM B196 UNS C17300 |
| Insulation | : PTFE per ASTM D1457 and ASTM D1710 |


Mechanical Specifications

Interface in accordance with : MIL-STD-348A

Environmental Specification

Operating Temperature : -65°C to +165°C

Diagram



| Dimensions | • | Millimetres | (Inches) |) |
|--------------|---|---------------|------------|---|
| Difficitions | • | Willin Hou Co | (Interies) | , |

| No. | Description | Material | Finish |
|-----|----------------|------------------|----------------|
| 1 | Body | Stainless Steel | Passivated |
| 2 | Insulation | PTFE | - |
| 3 | Centre Contact | Beryllium Copper | Gold 50µ" Min. |

Part Number Table

| Description | Part Number |
|--------------------------------------------------------------------|-------------|
| Straight SMA 2-Hole Flange Mount Field Jack Receptacle, 50Ω | MC002932 |

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage resulting from any reliance on the Information or use of it (including liability resulting from the negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

