Straight N Plug to BNC Jack Adaptor multicomp



Specifications

Adaptor Style Connector Type A Connector Type B

Electrical Specifications

Frequency Range Nominal Impedance Voltage Rating VSWR

Material Specifications Bodies

Centre Contact Insulation

: Brass per JIS-3604 : Beryllium Copper per ASTM B196 UNS C17300

: PTFE per ASTM D1457 and ASTM D1710

Mechanical Specifications

Interface in accordance with


: MIL-STD-348B

: -65°C to +165°C

Environmental Specifications

Operating Temperature

Diagram



Dimensions : Millimetres (Inches)

| No. | Description | Material | Finish |
|-----|----------------|------------------|-------------------|
| 1 | Shell | Brass | Nickel 100µ" Min. |
| 2 | Chassis | Brass | Nickel 100µ" Min. |
| 3 | Gasket | Silicone | - |
| 4 | Body | Brass | Nickel 100µ" Min. |
| 5 | Washer | Brass | - |
| 6 | Centre Contact | Beryllium Copper | Gold 3µ" Min. |
| 7 | Insulation | PTFE | - |

Part Number Table

: Straight Adaptor

: N Plug

: BNC Jack

: DC-6GHz

: 500V Max. : 1.2 Max.

: 75Ω

| Description | Part Number |
|---|-------------|
| Straight N Plug to BNC Jack Adaptor, 75Ω | MC002943 |

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com www.farnell.com www.newark.com

