



EZ2500 E-Ze Test™

Non-trip earth (phase-earth) loop impedance tester with PFC & PSC



A revolutionary 17th Edition tester with T-Safe™ non-trip P-E and P-N loop impedance tests, plus PFC and PSC checks.

The E-Ze Test™ performs:

- ◆ Non-trip loop tests, P-E and P-N
- ◆ Voltage test
- ◆ Socket test
- ◆ PFC and PSC test

Test readings scroll through in sequence on the clear, backlit, 32 character display to show socket problems or high / low voltage conditions. Then the loop impedance test results and PFC and PSC calculations are displayed.

SPECIFICATIONS

Nominal Voltage Rating: 220 V –250V AC, 50 Hz

Voltage Range for Wiring Error Detection: 30 - 275 V

Open Loop indication: If Open PE or PN Loop is detected, no Impedance Measurement takes place

High Earth indication:

3k to 70kΩ: “>3kΩ”

>70kΩ: “Open Earth”

Voltage Range for Impedance Measurement: 195 - 270 V

Frequency: 50 Hz

Non-Trip Earth Loop Impedance Ranges: 0.1-8.99Ω, 9.0-89.9Ω, 90-899Ω, 900-1699Ω, 1700-3000Ω

Phase Earth Loop Impedance Accuracy:

0.1 - 8.99Ω, ± 4% ± 0.05Ω *

9.0 - 89.9Ω, ± 5% ± 0.5Ω *

90 - 899Ω, ± 5% ± 5Ω *

900 - 1699Ω ± 5% ± 30Ω*

1700 - 3000Ω indicative

Phase Neutral Loop Impedance Accuracy:

0.1 - 8.99Ω, ± 4% ± 0.05Ω *

9.0 - 89.9Ω, ± 5% ± 0.5Ω *

90 - 899Ω, ± 5% ± 5Ω *

900 - 1699Ω ± 5% ± 30Ω *

1700 - 3000Ω indicative

Voltage Accuracy: ± 4 % **Frequency Accuracy:** ± 4 %

Temperature Range: -10° to 40° C at max 80 % Relative Humidity (Non-Condensing)

Power consumption:< 1.6 W **Weight:** 240g plus

Overtoltage category: CATIII/300V **Pollution degree:** 2

Supply: mains **Dimensions:** 145mm x 85mm x 53mm

Supplied with: zip carry case, mains lead & instructions

* **Note:-** Measurement accuracy can be affected by highly inductive or capacitive components distributed on the supply.

	EZ2500
Non-trip earth loop test	✓
Voltage test	✓
Socket test	✓
PSC test	✓
PFC test	✓
P-N test	✓
T-Safe™ technology	✓

Due to policy of continuous development, Martindale Electric reserves the right to alter equipment specification and description outlined in this document without prior notice. No part of this document shall be deemed to be part of any contract for the equipment unless specifically referred to as an inclusion within such contract. © Martindale Electric Co. Ltd. 2013

Martindale Electric Company Ltd.

Metrohm House, Imperial Park, Imperial Way, Watford, Hertfordshire, WD24 4PP, UK

Tel: 01923 441717 Fax: 01923 446900 E-mail: sales@martindale-electric.co.uk Web: www.martindale-electric.co.uk rev8