



The Klein Tools ET920 is a USB digital meter for Type-A and Type-C ports. It accurately and reliably measures and displays the USB port voltage, current, capacity, energy and resistance simultaneously. It can function with any USB-A and most USB-C ports, including Qualcomm Quick Charge® ports that have the ability to deliver power. It requires NO batteries as it draws power from the power source to function.

## Specifications

|                          |                                   |                            |   |
|--------------------------|-----------------------------------|----------------------------|---|
| <b>Type:</b>             | USB-A (Type A) and USB-C (Type C) | <b>Application:</b>        | USB Port Voltage, Current, Capacity, Energy and Resistance (Calculated) |
| <b>Special Features:</b> | Fits any USB-A and USB-C ports    | <b>Voltage:</b>            | 3 to 20V DC   |
| <b>Current:</b>          | USB-A: 0.05 to 3A; USB-C: 0.05-5A | <b>Capacity used:</b>      | 99999 mAh Maximum   |
| <b>Energy delivered:</b> | 999 Wh Maximum                    | <b>Resistance:</b>         | 400 Ohms Maximum  |
| <b>Elapsed time:</b>     | Up to 999 hours, 59 min, 59 secs  | <b>USB Compatibility:</b>  | USB-A, USB-C; Qualcomm Quick Charge® Compatible                         |
| <b>Drop Protection:</b>  | 2 m (6.6')                        | <b>Ingress protection:</b> | IP20  |
| <b>Display:</b>          | LCD                               | <b>Material:</b>           | Polymer   |
| <b>Overall Length:</b>   | 2.96" (75.2 mm)                   | <b>Overall Height:</b>     | 0.6" (15.2 mm)  |
| <b>Overall Width:</b>    | 1.96" (49.8 mm)                   | <b>Weight:</b>             | 1.7 oz (48 g)   |