
KEMET Part Number: VC0805K121R025



## KEMET, VC, Varistors, Low Voltage, 31 V, 25 VAC, 39 V, 65 V, 1 A, 120 A, 200 mJ, 5000 uW



| General information |                         |
|---------------------|-------------------------|
| Supplier:           | KEMET                   |
| Series:             | VC                      |
| Type:               | Varistors               |
| Style:              | SMD Chip                |
| Description:        | Surface Mount Varistors |
| Features:           | Low Voltage             |
| Termination:        | Nickel Tin              |
| RoHS:               | Yes                     |
|                     |                         |

| Dimensions |                 |  |
|------------|-----------------|--|
| Chip Size  | 0805            |  |
| L          | 2mm +/-0.25mm   |  |
| W          | 1.25mm +/-0.2mm |  |
| T          | 1.05mm MAX      |  |
| В          | 0.5mm +/-0.25mm |  |

| Specifications             |                        |
|----------------------------|------------------------|
| Voltage DC:                | 31 VDC (25C)           |
| Voltage AC:                | 25 VAC                 |
| Temperature Range:         | -55/+125C              |
| Storage Temperature Range: | -55/+150C              |
| Varistor Voltage:          | 39 VDC at 1 mA         |
| Clamping Voltage:          | 65 V                   |
| Clamping Current:          | 1 A (8/20 us MAX)      |
| Surge Current:             | 120 A (8/20 us MAX)    |
| Energy:                    | 0.2 J (10/1000 us MAX) |
| Capacitance:               | 260 pF (1kHz)          |

| Packaging Specifications |      |
|--------------------------|------|
| Packaging:               | T&R  |
| Packaging Quantity:      | 3500 |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

