# XVC4M35S

# 40mmTower ROGPole BuzzerFlash100-240VAC





#### Main

Range of product	Harmony XVC4	
Product or component type	Complete pre-wired monolithic tower light	
Beacon or indicator bank unit type3 illuminated units		
Sound signalling	Buzzer	
Mounting diameter	40 mm	
Component name	XVC	
Device short name	XVC	
Light source	Green LED steady or flashing Orange LED steady or flashing Red LED steady or flashing	
Supply circuit type	AC	
Noise level	7085 dB (continuous or intermittent tone) at 1 m	

## Complementary

Material	Polycarbonate (illuminated unit) ABS (acrylonitrile butadiene-styrene) (base unit) PBT + ABS (UL94-V0) (top cover) SGP (chromium-plated) (support tube)	
Mounting location	On support tube, 17 mm	
Product mounting	On support tube, 17 mm	
[Us] rated supply voltage	100240 V	
[Us] rated supply voltage	100240 V	
Cable cross section	0.33 mm <sup>2</sup> 0.83 mm <sup>2</sup>	
AWG gauge	AWG 18 AWG 22	;
Cable length	450 mm	
Marking	CE	
[Uimp] rated impulse withstand voltage	4 kV	
Current consumption	80 mA	
Fundamental frequency	2.23 kHz	
Flashing frequency	1 Hz	
Product weight	0.8 kg	
Height	637.2 mm	

### **Environment**

standards	EN/IEC 60947-1 EN/IEC 60947-5-1	
product certifications	UL	
protective treatment	TC	
ambient air temperature for storage	-3570 °C	
ambient air temperature for operation	-1050 °C	
electrical shock protection class	Class I conforming to EN/IEC 61140	
overvoltage category	Class I EN/IEC 61140	
IP degree of protection	IP23 in vertical surface installation conforming to EN/IEC 60529 IP54 in flat surface installation conforming to EN/IEC 60529	

## Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0808 - Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations


### Contractual warranty

	·
Warranty period	18 months

## Pre-assembled and Pre-wired Tower Light with Support Tube Mounting

#### **Dimensions**

Below drawing shows the maximum configuration of the product. Select the number of stages according to the product characteristics in order to get **b1** dimension.



No. of illuminated units	b1 Without buzzer (mm)	b1 Without buzzer (in.)
1 stage	567.20	22.33
2 stages	602.20	23.71
3 stages	637.20	25.09
4 stages	672.20	26.46
5 stages	707.20	27.84

# **Pre-assembled and Pre-wired Tower Light**

**Support Tube Mounting** 



