XU5N18NP341D

photo-electric sensor - XU5 - diffuse - Sn 0.10m - 12..24VDC - M12



Main

Range of product	OsiSense XU
Series name	Application food and beverage
Electronic sensor type	Photo-electric sensor
Sensor name	XU5
Sensor design	Cylindrical M18
Detection system	Diffuse
Material	Stainless steel
Line of sight type	Axial
Type of output signal	Discrete
Supply circuit type	DC
Wiring technique	3-wire
Discrete output type	NPN
Discrete output function	1 NO or 1 NC programmable
Electrical connection	1 male connector M12, 4 pins
Product specific application	-
Emission	Infrared diffuse
[Sn] nominal sensing distance	0.1 m diffuse

Complementary

Enclosure material	Stainless steel: 304 CU
Lens material	PMMA
Maximum sensing distance	0.15 m
Output type	Solid state
Add on output	Without
Add on input	Programmation
Status LED	1 LED (green) for supply on 1 LED (yellow) for output state
[Us] rated supply voltage	1224 V DC with reverse polarity protection
Supply voltage limits	1030 V DC
Switching capacity in mA	<= 100 mA (overload and short-circuit protection)
Switching frequency	<= 500 Hz
Voltage drop	<= 1.5 V (closed state)
Current consumption	<= 30 mA (no-load)
Delay first up	<= 15 ms
Delay response	<= 1 ms
Delay recovery	<= 1 ms
Setting-up	Without sensitivity adjustment
Diameter	18 mm
Length	72 mm
Product weight	0.065 kg

Environment

product certifications	CE CSA UL
ambient air temperature for operation	-2555 °C
ambient air temperature for storage	-4070 °C

vibration resistance	25 gn, amplitude = +/- 1.5 mm (f = 1055 Hz) conforming to IEC 60068-2-6
shock resistance	30 gn (duration = 11 ms) conforming to IEC 60068-2-27
IP degree of protection	IP67 conforming to IEC 60529


Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Compliant - since 1402 - Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold

Contractual warranty

Warranty period	18 months

Dimensions




(1) LED

Mounting and Clearance

Fixing nut tightening torque: < 15 N.m Connector tightening torque: 2 N.m

Wiring Schemes

M12 Connector




3: (-)

1: (+)

4: OUT/Output

2: Prog


3-wire, NPN NO or NC Programmable Function



Detection Curves

Diffuse System






(y) Ø of beam1: White 90%2: Grey 18%Object 10 x 10 cm

Excess Gain Curves (Ambient Temperature: + 25° C)

Diffuse System



(y) Gain(x) Distance (m)Object 10 x 10 cm

White 90%