Note: This datasheet may be out of date.
Please download the latest datasheet of PTGL09AR1R8H2B51B0 from the official website of Murata
Manufacturing Co., Ltd.

https://www.murata.com/en-eu/products/productdetail?partno=PTGL09AR1R8H2B51B0

PTGL09AR1R8H2B51B0













Appearance & Shape







(in mm)



- 1. Best suited to meet the requirements for power supplies and motor protection. Error-free operations are assured by rush current.
- 2. Circuit is protected until current is turned off.
- 3. Restores the original low resistance value automatically once the overload is removed.
- 4. Non-contact design leads to long life and no noise.

 Durable and strong against mechanical vibration and shock because it is a solid element.



| Limited Usage | Consumer Grade |
|---------------|--|
| Other Usage | Transformers Transistors Fluorescent Lamps |



Packaging Information

| Packaging | Specifications | Minimum Order Quantity |
|-----------|----------------|---------------------------|
| В0 | Bulk(Bag) | 500 |

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/11/25

Note: This datasheet may be out of date $\underline{ \text{Please download the latest datasheet of PTGL09AR1R8H2B51B0 from the official website of Murata} \\$

Manufacturing Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=PTGL09AR1R8H2B51B0

PTGL09AR1R8H2B51B0



| Max. Voltage | 30V |
|---------------------------------------|---------------|
| Hold Current | 410mA |
| Measure Condition of Hold Current | (at +60°C) |
| Hold Current (2) | 510mA |
| Measure Condition of Hold Current (2) | (at +25°C) |
| Trip Current | 970mA |
| Measure Condition of Trip Current | (at +25°C) |
| Trip Current(2) | 1120mA |
| Measure Condition of Trip Current(2) | (at -10°C) |
| Max. Current | 3A |
| Resistance (25°C) | 1.8Ω |
| Resistance Value Tolerance (at 25°C) | ±25% |
| Power Consumption(typ) | 1.8W |
| Operating Temperature Range | -10°C to 60°C |
| D: Outer Dimension | 9.5mm |
| Thickness | 4mm |
| F: Lead Space | 5mm |

| d: Lead Diameter | 0.6mm |
|------------------|-------|
| Shape | Lead |
| Mass | 0.47g |
| Mass | 0.47g |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





URL: https://www.murata.com/

Last updated :2019/11/25


PTGL09AR1R8H2B51B0







Resistance-Temperature Charac.



Protective Threshold Current Range

Operating Time (Typical Curve)

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/11/25