muRata Inductor Data Sheet

LQG15HZ82NG02# "#" indicates a package specification code.



< List of part numbers with package codes >

LQG15HZ82NG02D , LQG15HZ82NG02J , LQG15HZ82NG02B



0.25+0.1 0.5±0.05 0.5±0.05 1.0±0.05 (in mm) 1.0 ±0.05mm L size

0.5 ±0.05mm

0.5 ±0.05mm

0402 (1005)

References
References

Packaging code	Specifications	Minimum quantity
D	φ180mm Paper taping	10000
J	φ330mm Paper taping	50000
В	Packing in bulk	1000

Mass (Тур.)
1 piece	0.001g

Specifications

Size code in inch (mm)

W size

T size

Inductance	82nH ±2%
Inductance test frequency	100MHz
Rated current (Itemp) (Based on Temperature rise)	200mA
Max. of DC resistance	1.20Ω
Q (min.)	8
Q test frequency	100MHz
Self resonance frequency (min.)	700MHz
Operating temperature range (Self-temperature rise is not included)	-55°C to 125°C
Series	LQG15HZ_02

🔔 Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.


Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Chart of characteristic data (The charts below may show another part number which shares its characteristics.)

Ó.

Frequency[GHz]



2 of 2

0

🔔 Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.